

SmartOnline S3MT-Series 3-Phase 100kVA Input (480V to 208V)/Output (208V to 480V) Isolation Transformers

MODEL NUMBER: **S3MT-100KWR480V**



Enclosure with step-down and step-up transformers offers line isolation and protection to the connected 3-phase UPS and its load.

Features

Get Complete Step-Down/Step-Up and Isolation Protection

Tripp Lite's S3MT-100KWR480V includes two transformers in a single cabinet: a 480V (Delta) to 208V (Wye) input isolation step-down transformer and a 208V (Wye) to 480V (Wye) output auto step-up transformer. It isolates the UPS and connected components from line surges and spikes caused by utility power disruptions that can damage equipment or corrupt data. The dual transformers are ideal for 4-wire (3Ph+N+PE) loads in government, manufacturing, healthcare and corporate settings with 480V electrical mains and 480V IT loads.

Performs with High Efficiency up to 97.8%

Not only is the S3MT-100KWR480V wrap-around transformer very efficient, with up to 97.8 percent efficiency, but it is also very quiet with a noise profile less than 65 dBA. Built-in circuit breakers on both transformers help prevent dangerous power overloads. Eight ball-bearing cooling fans help prevent overheating. An overheat-sensing relay and switch combine with red alarm indicators to provide over-temperature warning and overheating protection.

Small Footprint for Quick Installation in a Compact Space

The compact footprint enables installation of the S3MT-100KWR480V with minimal space. The rugged stainless steel housing ships ready for immediate tower installation with a compatible 80–100kVA/kW Tripp Lite S3M-Series 3-phase UPS system.

Highlights

- Dual 100kVA/kW 480V transformers for government, healthcare and corporate settings
- Up to 97.8% efficiency with a quiet acoustic profile less than 65 dBA
- Resettable protection relay/switch and red alarm indicators warn against overheating
- Rugged stainless steel housing with compact footprint comes ready for installation
- Compatible with select 80–100kVA/kW Tripp Lite S3M-Series 208V 3-phase UPS systems

Applications

Protect equipment in government, healthcare, manufacturing, corporate and other settings that have 480V electrical mains and 480V IT loads

System Requirements

80–100kVA/kW Tripp Lite S3M-Series 208V 3-phase UPS system

Package Includes

- S3MT-100KWR480V 3-Phase 100kVA Input/Output Isolation Transformers
- (4) Bottom skirts
- (24) Screws
- Owner's manual

Specifications

OVERVIEW	
UPC Code	037332253217
Efficiency	96.7% @ full load



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Nominal Voltage / Frequency	Input transformers (T-in) 480V / Output transformer (T-out) 208V, 3-PH / 60Hz
VA / Watt Capacity	100000
Transformer Type	Dry type, Input step-down isolation transformer and Output step-up Auto Transformer
INPUT	
Nominal Input Voltage(s) Supported	480V 3-PH Delta
UPS Input Connection Type	Hardwire
Input Phase	3-Phase
OUTPUT	
Output Volt Amp Capacity (VA)	100000
Output Capacity (kVA)	100
Nominal Output Voltage(s) Supported	480V 3-PH Wye
Output Receptacles	Hardwire
PHYSICAL	
Primary Form Factor	Tower
Cooling Method	8 x BALL BEARING, 172x152mm (1928 TOTAL CFM)
Form Factors Supported	Tower
Shipping Dimensions (hwd / in.)	85.40 x 27.60 x 37.80
Shipping Weight (kg)	939.84
Unit Dimensions (hwd / in.)	77.6 x 23.6 x 33.5
Unit Dimensions (hwd / cm)	197.1 x 60 x 85
Unit Weight (lbs.)	1960
Unit Weight (kg)	889.04
ENVIRONMENTAL	
Heat Dissipation (BTU/Hr) @ Full Load	22526
INPUT TRANSFORMER	
Input Voltage	480V 3-PH Delta
Input Voltage Range	(-45%, +25%) for 40% load (-20%, +25%) for 100% load
Input Amp(s)	168 A
AC Input Configuration	Delta
AC Input Frequency	50/60
Frequency Range	40/70Hz



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Voltage Selection	NONE
Input Inrush Current	1450 A
VA Rating	100K
Input Number of Phases	3PH
AC Output Voltage (V)	120/208V 3-PH Wye
AC Output Amps	374 A
Output Number of Phases	3PH + N
AC Output Configuration	WYE
Output Isolation	Yes
Output Breaker Rating	400 A
Connection Type	COPPER BAR
LED Warning Light Functions	The over-temperature warning LED light will turn ON when the output/secondary of the Input transformer reaches 160°C \pm 5°C and will turn OFF when the corresponding transformer cools down to 125°C \pm 5°C
Over Temperature Reset	The transformers include an over-temperature protection relay and thermal switch on the secondary sides of the input (T-in) transformer and on the primary side of the output (T-out) transformer to protect the transformer from overheating. Thermal switches on input and output transformers will open the corresponding transformer breaker if either of the transformer reaches 155°C/311°F to 165°C/329°F. Once the transformer cools down to 120°C/248°F to 130°C/266°F, the corresponding warning LED light will turn OFF, and the corresponding transformer breaker may be closed to restart operation.
Efficiency @ Half Load	97.80%
Efficiency @ Full Load	96.70%
Heat Dissipation (BTU/Hr) @ Full Load	22526
Audible Noise (dBA @ 1m)	65dB max

OUTPUT TRANSFORMER

Input Voltage	120/208V 3-PH Wye
Input Voltage Range	(-45%,+25%)for 40 % load (-20%,+25%)for 100 % load
Input Amp(s)	287 A
AC Input Configuration	WYE
AC Input Frequency	50/60 HZ
Frequency Range	40-70HZ
Input Inrush Current	3330 A
Input Number of Phases	3PH+N
VA Rating	100K
AC Output Voltage (V)	480V 3-PH Wye
AC Output Amps	120 A
Output Number of Phases	3PH+N
AC Output Configuration	WYE



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Output Isolation	No
Output Breaker Rating	400 A
Connection Type	COPPER BAR
LED Warning Light Functions	The over-temperature warning LED light will turn ON when the input/primary of the Output transformer reaches 160°C ±5°C and will turn OFF when the corresponding transformer cools down to 125°C ±5°C
Over Temperature Reset	The transformers include an over-temperature protection relay and thermal switch on the secondary sides of the input (T-in) transformer and on the primary side of the output (T-out) transformer to protect the transformer from overheating. Thermal switches on input and output transformers will open the corresponding transformer breaker if either of the transformer reaches 155°C/311°F to 165°C/329°F. Once the transformer cools down to 120°C/248°F to 130°C/266°F, the corresponding warning LED light will turn OFF, and the corresponding transformer breaker maybe closed to restart operation.
Efficiency @ Half Load	97.80%
Efficiency @ Full Load	96.70%
Heat Dissipation (BTU/Hr) @ Full Load	22526
Audible Noise (dBA @ 1m)	65dB max
WARRANTY	
Product Warranty Period (Worldwide)	2-year limited warranty
Product Warranty Period (U.S. & Canada)	2-year limited warranty

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <https://www.tripplite.com/products/product-certification-agencies>