



PEL-2000 Series

FEATURES

- 10 sets of Preset Memory
- Parallel Operation for Increased Capacity
- Sequence Function to Enable Load Simulations
- External Waveform Control Functions
- High Precision and High Resolution
- Variable Slew Rate
- Multi-Channel System up to 8 Channel Outputs
- Parallel Operation for Increased Capacity
- Sequence Function to Enable Load Simulations
- External Waveform Control Functions
- Delay Control
- OPP/OCP/OVP/OTP Protection all Level Could be Change
- Multi-Interface USB Device/Host, RS-232C, GPIB (Optional)
- 120 Sets Setup Memory

In high volume manufacturing requires optimization of test system throughput, to maximize production volume without increasing floor space. The PEL-2000 Series electronic loads can help you in a number of ways to achieve this goal.

The PEL-2000 Series that the current trend in semiconductors is towards lower voltages and higher speeds. This trend places similar demands on both the components of semiconductor power units, such as switching power supplies, batteries and DC/DC converters, and also on the electronic loads used for testing. The advent of an electronic load system that satisfies all these needs has been long awaited. The PEL-2000 Series of compact and high-performance modular electronic loads is capable of operating in CC/CR/CV mode. The load system consists of load modules and a main frame. The load modules are inserted into the main frame that also serves as a master unit. The PEL-2002 frame can accommodate up to two load modules, while the PEL-2004 frame can accommodate up to four. The PEL-2000 Series it has including variable slew rate, a switching function, 10 preset memory function, 120 sets setup memories, and a sequence function. For communication, the system is provided with USB and RS-232C interfaces as standard otherwise it also has optional GPIB Interface. Both of RS-232C and GPIB those interfaces support IEEE 488.2 as well as the Standard Commands for Programmable Instruments (SCPI) commands, developed for testing and measuring instruments.

Programmable delay allows for either simultaneous or sequential load changes: This is the most efficient way to conduct testing of multiple output DC power supplies, simulating real-life loading patterns, with a minimum of programming commands.

Increase System Flexibility for future requirements that the most of power supply and battery charger test systems designed today need to test a variety of products and assemblies. In the future, additional products or assemblies may be needed. A flexible family of electronic loads makes present system design and future growth much easier.

When customer were testing high current power supplies that electronic load modules can be operated in parallel to provide addition current sinking capability. There are also have analog control programming and monitoring ports for those applications that utilize as standard interfaces, require custom waveforms, or utilize process control signals.

For a CV power supply, measurement of the output voltage and input voltage should be made after the load is varied from the minimum to the full current rating of the power supply under test. Measurement of the AC input voltage is necessary to ensure that the output voltage change is a result of only the load change, and not from a change in the ac input. To decrease the test time when test throughput is a concern, a regulated AC source providing a predetermined AC input level and frequency can be utilized. This will eliminate the need for the ac input voltage measurement. The output voltage should be allowed the specified settling time before measurements are taken. An electronic load selected for this test must be capable of operating in CC or CR mode, and must have input ratings (voltage, current, and power) sufficient to accommodate the maximum ratings of the power supply under test.

APPLICATIONS

- R & D Design and Verification for :
Switching Power Supply 、 Server Power 、 AC/DC Adaptor 、 AC/DC Power Module 、 Power IC 、 DC/DC Power Module 、 Fuse 、 Battery 、 Automotive Wire 、 Switch/Relay
- Laboratories and Educational Facilities
- Product Testing and Quality Assurance

SPECIFICATIONS

	PEL-2020		PEL-2030			PEL-2040		PEL-2041		
CHANEL	L/R	L/R	Left	Right	Right	-	-	-	-	
POWER	Low	High	N/A	Low	High	Low	High	Low	High	
CURRENT	100W	100W	30W	250W	250W	350W	350W	350W	350W	
VOLTAGE	0~2A	0~20A	0~5A	0~4A	0~40A	0~7A	0~70A	0~1A	0~10A	
MIN.OPERATING VOLTAGE(dc)	1~80V	1~80V	1~80V	1~80V	1~80V	1~80V	1~80V	2.5~500V	2.5~500V	
	1.0V at 2A	1.0V at 20A	1.0V at 5A	1.0V at 4A	1.0V at 40A	1.0V at 7A	1V at 70A	2.5V at 1A	2.5V at 10A	
STATIC MODE										
CONSTANT CURRENT MODE	0~2A		0~5A		0~40A		0~7A		0~10A	
Resolution	0.5mA		1.25mA		1mA		1mA		0.2mA	
Accuracy	±(0.1%set + 0.1%F.S.)		±(0.1%set + 0.1%F.S.)		±(0.1%set + 0.2%F.S.)		±(0.1%set + 0.2%F.S.)		±(0.1%set + 0.2%F.S.)	
CONSTANT RESISTANCE MODE	0.075Ω~300Ω		0.3Ω~1.2KΩ		0.0375Ω~150Ω		0.025Ω~100Ω		1.25Ω~5KΩ	
Resolution	(100W/16V)		(30W/16V)		(250W/16V)		(350W/16V)		(350W/125V)	
Accuracy	3.75Ω~15K		15Ω~60K		1.875Ω~7.5K		1.25Ω~5K		50Ω~200K	
	(100W/80V)		(30W/80V)		(250W/80V)		(350W/80V)		(350W/500V)	
	12bits		12bits		12bits		12bits		12bits	
	300Ω: ±(0.2%set+0.1%)		12KΩ: ±(0.2%set+0.1%)		150Ω: ±(0.2%set+0.1%)		100Ω: ±(0.2%set+0.1%)		5KΩ: ±(0.2%set+0.02%)	
	15KΩ: ±(0.1%set+0.02%)		60KΩ: ±(0.1%set+0.01%)		7.5KΩ: ±(0.1%set+0.02%)		5KΩ: ±(0.1%set+0.02%)		200KΩ: ±(0.1%set+0.01%)	
	With ≥ 2.5V at input		With ≥ 2.5V at input		With ≥ 2.5V at input		With ≥ 2.5V at input		With ≥ 5V at input	
CONSTANT VOLTAGE MODE	1~80V		1~80V		1~80V		1~80V		2.5~500V	
Resolution	20mV		20mV		20mV		20mV		100mV	
Accuracy	±(0.05%set+0.1%F.S.)		±(0.05%set+0.1%F.S.)		±(0.05%set+0.1%F.S.)		±(0.05%set+0.1%F.S.)		±(0.05%set+0.1%F.S.)	
DYNAMIC MODE										
CONSTANT CURRENT MODE T1&T2	0.025mS~10mS/Res:1μS		0.025mS~10mS/Res:1μS			0.025mS~10mS/Res:1μS		0.025mS~10mS/Res:1μS		
Accuracy	1mS ~ 30S / Res : 1mS		1mS ~ 30S / Res : 1mS			1mS ~ 30S / Res : 1mS		1mS ~ 30S / Res : 1mS		
	1μS / 1mS ± 100ppm		1μS / 1mS ± 100ppm			1μS / 1mS ± 100ppm		1μS / 1mS ± 100ppm		
Slew Rate(±10%set+15μS)	0.32~80mA/μS		0.8~200mA/μS		0.64~160mA/μS		0.001~0.28A/μS		0.16~40mA/μS	
Slew Rate Resolution	0.32mA/μS		0.8mA/μS		0.64mA/μS		0.001A/μS		0.16mA/μS	
Current	0~2A		0~5A		0~4A		0~7A		0~1A	
Current Resolution	0.5mA		1.25mA		1mA		1mA		0.2mA	
Current Accuracy	±0.4% F.S.		±0.4% F.S.		±0.4% F.S.		±0.4% F.S.		±0.4% F.S.	
MEASUREMENT										
VOLTAGE READBACK	0~16V		0~16V,0~80V		0~16V		0~16V		0~125V	
Resolution	0.5mV		0.5mV,2.5mV		0.5mV		0.5mV		4mV	
Accuracy	±(0.05%set +0.05%F.S.)		±(0.05%set +0.05%F.S.)		±(0.05%set +0.05%F.S.)		±(0.05%set +0.05%F.S.)		±(0.05%set +0.05%F.S.)	
CURRENT READBACK	0~2A		0~5A		0~4A		0~7A		0~1A	
Resolution	0.0625mA		0.15625mA		0.125mA		0.175mA		0.032mA	
Accuracy	±(0.1%set +0.1%F.S.)		±(0.1%set +0.1%F.S.)		±(0.1%set +0.1%F.S.)		±(0.1%set +0.1%F.S.)		±(0.1%set +0.1%F.S.)	
PROTECTIVE										
Over Power Protection (±2%set+0.25%F.S.)	1~102W		1~30.6W		1~255W		1~357W		1~357W	
Resolution	0.5W		0.15W		1.25W		1.75W		1.75W	
Over Current Protection (±2%set+0.25%F.S.)	0~20.4A		0~5.1A		0~40.8A		0~71.4A		0~10.2A	
Resolution	0.05A		0.0125A		0.1A		0.175A		0.025A	
Over Voltage Protection (±2%set+0.25%F.S.)	1~81.6V		1~81.6V		1~81.6V		1~81.6V		1~510V	
Resolution	0.2V		0.2V		0.2V		0.2V		1.25V	
Over Temperature Protection	≈ 85°C		≈ 85°C		≈ 85°C		≈ 85°C		≈ 85°C	
Rated Power Protection (±2%set)	110W		33W		275W		385W		385W	
GENERAL										
SHORT CIRCUIT	≈ 2.2/2A		≈ 5.5/5A		≈ 4.4/4A		≈ 7.7/7A		≈ 1.1/1A	
Current(CC)	≈ 22/20A		≈ 15Ω, ≈ 0.3Ω		≈ 1.875Ω		≈ 0.0375Ω		≈ 0V	
Voltage(CV)	≈ 3.75Ω		≈ 0.075Ω		≈ 0.075Ω		≈ 0.025Ω		≈ 50Ω	
Resistance(CR)	800KΩ (Typical)		800KΩ (Typical)			800KΩ (Typical)		800KΩ (Typical)		
INPUT RESISTANCE(LOAD OFF)	800KΩ (Typical)		800KΩ (Typical)			800KΩ (Typical)		800KΩ (Typical)		
WEIGHT	Approx. 3.8 kg									
DIMENSIONS & WEIGHT(PEL-202)	272 mm (W) X 200 mm (H) X 581 mm (D) ; Approx. 16.1kg (full modules)									
DIMENSIONS & WEIGHT(PEL-2004)	435 mm (W) X 200 mm (H) X 581 mm (D) ; Approx. 24.8kg (full modules)									

Specifications subject to change without notice. EL-2000GD1DH

ORDERING INFORMATION

PEL-2002 Mainframe For Two Load Module
PEL-2004 Mainframe For Four Load Module
PEL-2020 Programmable D.C. Electronic Load Module
PEL-2030 Programmable D.C. Electronic Load Module
PEL-2040 Programmable D.C. Electronic Load Module
PEL-2041 Programmable D.C. Electronic Load Module

Note : Load module can't be used without mainframe

ACCESSORIES

PEL-2002/2004
 User manual x1, Power cord x1
PEL-2020/2030/2040/2041
 GTL-120 Test lead x 1, GTL-121 Sense lead x 1

OPTIONAL ASSESSORIES

PEL-001 GPIB card **PEL-003** Panel cover **GTL-248** GPIB cable
PEL-002 PEL-2004 Rack mount kit **GTL-246** USB cable **GTL-249** Frame link cable

Global Headquarters

GOOD WILL INSTRUMENT CO., LTD.

No. 7-1, Jhongsing Road, Tucheng City, Taipei County 236, Taiwan
 T +886-2-2268-0389 F +886-2-2268-0639
 E-mail: marketing@goodwill.com.tw

China Subsidiary

INSTEK ELECTRONIC (SHANGHAI) CO., LTD.

8F, of NO.2 Building, No.889 Yishan Road, Shanghai China
 T +86-21-6485-3399 F +86-21-5450-0789
 E-mail: marketing@instek.com.cn

Malaysia Subsidiary

GOOD WILL INSTRUMENT (M) SDN. BHD.

27, Persiaran Mahsuri 1/1, Sunway Tunas,
 11900 Bayan Lepas, Penang, Malaysia.
 T +604-6309988 F +604-6309989
 E-mail: sales@goodwill.com.my

U.S.A. Subsidiary

INSTEK AMERICA CORP.

3661 Walnut Avenue Chino, CA 91710, U.S.A.
 T +1-909-5918358 F +1-909-5912280
 E-mail: sales@instekamerica.com

Japan Subsidiary

INSTEK JAPAN CORPORATION

4F, Prosper Bldg, 1-3-3 Iwamoto-Cho Chiyoda-Ku,
 Tokyo 101-0032 Japan
 T +81-3-5823-5656 F +81-3-5823-5655
 E-mail: info@instek.co.jp

Korea Subsidiary

GOOD WILL INSTRUMENT KOREA CO., LTD.

Room No.805, Ace Hightech-City B/D 1Dong,
 Mullaee-Dong 3Ga 55-20, Yeongduengpo-Gu, Seoul, Korea
 T +82 2 3439 2205 F +82 2 3439 2207
 E-mail: gwinstek@gwinstek.co.kr

GW INSTEK

www.gwinstek.com