



www.armadatech.com • (616) 803-1080

Pro95i™ Advanced AC Leakage Clamp Multimeter



Pro95i™ Features

- Measures AC Line Current in milliamps
- Measures AC or DC voltage, AC current, and resistance
- True RMS
- Alligator Clips Included
- Auto-Ranging Measurement
- Backlit Digital Screen
- Compact, Solid Design

PRODUCT DESCRIPTION

The Pro95i™ Advanced AC Leakage Clamp Multimeter is perfect for 2-wire troubleshooting. The Pro95i makes it possible to diagnose cable and equipment faults in 2-wire systems without opening splices. The Pro95i measures AC line current with a resolution of 1 microampere simply by clamping over wires in a control cable. In addition, VAC, VDC, and ohms measurements are available. All utilize a built-in auto ranging function for easy use.

PRODUCT FEATURES

- Contactless measurement of line currents down to 5 microamperes, a critical and necessary feature in diagnosing 2-wire faults
- True RMS measurement with automatic signal smoothing for improved accuracy
- Auto-off after 30 minutes idle
- Back-lit screen for dark areas

SPECIFICATIONS

Current: Range from 5 microamperes to 60 amperes AC; Resolution to 1 microampere
Voltage: VAC to 600V VDC to 600V
Resistance: Automatically reads 0 to 600 Kohms, with selectable beep short circuit check
Weight: Less than 1 lb. with packaging

PACKAGE INCLUDES

- Pro95i™ Meter
- Carrying Case
- Test Probes with attachable alligator clips
- Instructions with a multilingual quick reference card
- Batteries

ORDERING INFORMATION

CAT NO.	DESCRIPTION	QUANTITY
Pro95i™	Advanced AC Leakage Clamp Multimeter	1

Distributed by:



For more information contact:

Armada Technologies®

3596 76th St. SE
Caledonia, MI 49316

Phone: (616) 803-1080

Fax: (616) 803-1083

www.armadatech.com