

SAMPLE

検査成績表

<TEST REPORT>

品名<Model Name> (パワーメータ<POWER METER>)
 形名<Model Number> (PW3335-03)
 製造番号<Serial No.> (No. 260188888)
 検査年月日<Test Date> (2026-01-27)
 <YYYY-MM-DD>
 検査条件<Test Conditions> (23.0 °C, 41 %rh)

1. 測定精度<Measurement Accuracy>

項目	レクティ ファイア	レンジ	入力<Input>		許容範囲		校正値 *1				
<Item>	<Rect>	<Range>	<Volt>	<Freq>	<Tolerance>		<Calibration Value>				
-1. 電圧<Voltage>											
AC+DC		1000V	1kV	55Hz	0.9985 kV	~	1.0015 kV	(	1.0000 kV)		
		600V	600V	55Hz	599.10 V	~	600.90 V	(	599.98 V)		
		300V	300V	55Hz	299.55 V	~	300.45 V	(	299.99 V)		
		150V	150V	55Hz	149.78 V	~	150.22 V	(	150.00 V)		
			100V	55Hz	99.85 V	~	100.15 V	(	100.00 V)		
			1.5V	55Hz	1.43 V	~	1.57 V	(	1.50 V)		
		60V	60V	55Hz	59.910 V	~	60.090 V	(	59.993 V)		
		30V	30V	55Hz	29.955 V	~	30.045 V	(	29.999 V)		
		15V	15V	55Hz	14.978 V	~	15.022 V	(	14.999 V)		
		6V	6V	55Hz	5.9910 V	~	6.0090 V	(	5.9993 V)		
			0V	-	0.0000 V	~	0.0000 V	(	0.0000 V)		
		DC	1000V	+1kV			0.9980 kV	~	1.0020 kV	(	1.0000 kV)
				0V			0.0000 kV	~	0.0000 kV	(	0.0000 kV)
			600V	+600V			598.80 V	~	601.20 V	(	600.05 V)
				0V			0.00 V	~	0.00 V	(	0.00 V)
	300V		+300V			299.40 V	~	300.60 V	(	300.03 V)	
			0V			0.00 V	~	0.00 V	(	0.00 V)	
	150V		+150V			149.70 V	~	150.30 V	(	150.00 V)	
			0V			0.00 V	~	0.00 V	(	0.00 V)	
	60V		+60V			59.880 V	~	60.120 V	(	60.003 V)	
			0V			0.000 V	~	0.000 V	(	0.000 V)	
	30V		+30V			29.940 V	~	30.060 V	(	30.001 V)	
			0V			0.000 V	~	0.000 V	(	0.000 V)	
	15V		+15V			14.970 V	~	15.030 V	(	15.000 V)	
			0V			0.000 V	~	0.000 V	(	0.000 V)	
	6V	+6V			5.9880 V	~	6.0120 V	(	5.9998 V)		
		+0.06V			0.0540 V	~	0.0660 V	(	0.0599 V)		
		0V			0.0000 V	~	0.0000 V	(	0.0000 V)		
		-6V			-6.0120 V	~	-5.9880 V	(	-6.0000 V)		

備考<Note>

・特に設定の明記のない場合、以下の設定で検査しています。

結線: 1P2W, VT比: 1, CT比: 1, ゼロクロスフィルタ: 500Hz

<Inspection settings are as follows except noted.

Wiring: 1P2W, VT Ratio: 1, CT Ratio: 1, Filter(Zero Cross): 500Hz>

*1. FAIL判定箇所は、グレー表示としています。<FAIL decision points are highlighted in gray.>

*2. 電流入力は、外部センサの入力に比例した電圧入力にて行います。

<Current input value is indicated and executed by voltage in proportion to the input for External Sensor.>

総合判定<Overall Result>

(**PASS**)

発行責任者: 生産本部長

<Approved by>

<Director of Manufacturing Division>

(*Tsutomu Mandai*)

Tsutomu Mandai

SAMPLE

検査成績表

<TEST REPORT>

製造番号<Serial No.> (No. 260188888)
検査年月日<Test Date> (2026-01-27)
(<YYYY-MM-DD>)

項目	レクティ ファイア	レンジ	入力<Input>		許容範囲		校正値 *1			
<Item>	<Rect>	<Range>	<Curr>	<Freq>	<Tolerance>		<Calibration Value>			
-2. 電流<Current>										
AC+DC	B (20A)	20A	20A	55Hz	19.970 A	~	20.030 A	(19.999 A)		
		20A	20A	55Hz	19.970 A	~	20.030 A	(20.000 A)		
		10A	10A	55Hz	9.985 A	~	10.015 A	(10.000 A)		
		5A	5A	55Hz	4.9925 A	~	5.0075 A	(5.0001 A)		
		2A	2A	55Hz	1.9970 A	~	2.0030 A	(2.0000 A)		
		1A	1A	55Hz	0.9985 A	~	1.0015 A	(1.0000 A)		
		500mA	500mA	55Hz	499.25 mA	~	500.75 mA	(500.03 mA)		
		200mA	200mA	55Hz	199.70 mA	~	200.30 mA	(200.05 mA)		
			100mA	55Hz	99.85 mA	~	100.15 mA	(100.00 mA)		
			2mA	55Hz	1.90 mA	~	2.10 mA	(2.00 mA)		
			0A	-	0.00 mA	~	0.00 mA	(0.00 mA)		
		100mA	100mA	55Hz	99.85 mA	~	100.15 mA	(100.00 mA)		
		50mA	50mA	55Hz	49.925 mA	~	50.075 mA	(49.996 mA)		
		20mA	20mA	55Hz	19.970 mA	~	20.030 mA	(19.998 mA)		
		10mA	10mA	55Hz	9.985 mA	~	10.015 mA	(9.999 mA)		
		5mA	5mA	55Hz	4.9925 mA	~	5.0075 mA	(4.9998 mA)		
		2mA	2mA	55Hz	1.9960 mA	~	2.0040 mA	(2.0001 mA)		
		1mA	1mA	55Hz	0.9975 mA	~	1.0025 mA	(1.0001 mA)		
			0.03mA	55Hz	0.0285 mA	~	0.0315 mA	(0.0301 mA)		
			0mA	-	0.0000 mA	~	0.0000 mA	(0.0000 mA)		
		DC	B (20A)	+20A			19.959 A	~	20.041 A	(19.996 A)
				0A			0.000 A	~	0.000 A	(0.000 A)
				20A	+20A		19.959 A	~	20.041 A	(19.998 A)
					0A		0.000 A	~	0.000 A	(0.000 A)
				10A	+10A		9.979 A	~	10.021 A	(10.002 A)
					0A		0.000 A	~	0.000 A	(0.000 A)
				5A	+5A		4.9890 A	~	5.0110 A	(5.0008 A)
					0A		0.0000 A	~	0.0000 A	(0.0000 A)
				2A	+2A		1.9950 A	~	2.0050 A	(2.0002 A)
					0A		0.0000 A	~	0.0000 A	(0.0000 A)
				1A	+1A		0.9970 A	~	1.0030 A	(1.0001 A)
					0A		0.0000 A	~	0.0000 A	(0.0000 A)
				500mA	+500mA		498.00 mA	~	502.00 mA	(500.03 mA)
	0A				0.00 mA	~	0.00 mA	(0.00 mA)		
200mA	+200mA				198.60 mA	~	201.40 mA	(200.03 mA)		
	0A				0.00 mA	~	0.00 mA	(0.00 mA)		
	-200mA				-201.40 mA	~	-198.60 mA	(-200.00 mA)		
100mA	+100mA				99.79 mA	~	100.21 mA	(100.01 mA)		
	0A				0.00 mA	~	0.00 mA	(0.00 mA)		
50mA	+50mA				49.890 mA	~	50.110 mA	(50.001 mA)		
	0A				0.000 mA	~	0.000 mA	(0.000 mA)		
20mA	+20mA				19.950 mA	~	20.050 mA	(19.998 mA)		
	0A				0.000 mA	~	0.000 mA	(0.000 mA)		
10mA	+10mA				9.970 mA	~	10.030 mA	(9.999 mA)		
	0A				0.000 mA	~	0.000 mA	(0.000 mA)		
5mA	+5mA				4.9800 mA	~	5.0200 mA	(4.9999 mA)		
	0A				0.0000 mA	~	0.0000 mA	(0.0000 mA)		

SAMPLE

検査成績表

<TEST REPORT>

製造番号<Serial No.> (No. 260188888)
検査年月日<Test Date> (2026-01-27)
(<YYYY-MM-DD>)

項目	レクティ ファイア	レンジ	入力<Input>	許容範囲	校正値 *1
<Item>	<Rect>	<Range>	<Curr> <Freq>	<Tolerance>	<Calibration Value>
		2mA	+2mA	1.9860 mA ~ 2.0140 mA	(2.0003 mA)
			0A	0.0000 mA ~ 0.0000 mA	(0.0000 mA)
		1mA	+1mA	0.9880 mA ~ 1.0120 mA	(1.0000 mA)
			+0.01mA	-0.0010 mA ~ 0.0210 mA	(0.0099 mA)
			0A	0.0000 mA ~ 0.0000 mA	(0.0000 mA)
			-1mA	-1.0120 mA ~ -0.9880 mA	(-1.0000 mA)

項目	レクティ ファイア	レンジ	入力<Input>	許容範囲	校正値 *1
<Item>	<Rect>	<Range>	<Volt/Curr/Pow/Freq/PF>	<Tolerance>	<Calibration Value>

-3. 有効電力 力率 1<Power PF=1>

AC+DC	150V /200mA	150V, 200mA, 30W, 55Hz, PF=1	29.955 W ~ 30.045 W	(30.003 W)
		150V, 100mA, 15W, 55Hz, PF=1	14.978 W ~ 15.022 W	(15.000 W)
		150V, 2mA, 0.3W, 55Hz, PF=1	0.285 W ~ 0.315 W	(0.300 W)
		150V(55Hz), 0A, 0W, -, -	-0.015 W ~ 0.015 W	(0.001 W)
	1000V /20A	1000V, 20A, 20kW, 55Hz, PF=1	19.970 kW ~ 20.030 kW	(20.000 kW)
	1000V /1mA	1000V, 1mA, 1W, 55Hz, PF=1	0.9975 W ~ 1.0025 W	(1.0000 W)
	6V /20A	6V, 20A, 120W, 55Hz, PF=1	119.82 W ~ 120.18 W	(120.00 W)
	6V /1mA	6V, 1mA, 6mW, 55Hz, PF=1	5.9850 mW ~ 6.0150 mW	(6.0001 mW)
		6V(55Hz), 0A, 0W, -, -	-0.0090 mW ~ 0.0090 mW	(-0.0003 mW)
DC	6V /1mA	+6V, +1mA, +6mW	5.9280 mW ~ 6.0720 mW	(5.9998 mW)
		-6V, -1mA, +6mW	5.9280 mW ~ 6.0720 mW	(5.9997 mW)
		+6V, +10μA, +0.06mW	-0.0060 mW ~ 0.1260 mW	(0.0593 mW)
		0V, 0A, 0W	-0.0060 mW ~ 0.0060 mW	(0.0000 mW)
	1000V /20A	+1000V, +20A, +20kW	19.959 kW ~ 20.041 kW	(19.999 kW)
		-1000V, -20A, +20kW	19.959 kW ~ 20.041 kW	(19.988 kW)

項目	レクティ ファイア	レンジ	入力<Input>	許容範囲	校正値 *1
<Item>	<Rect>	<Range>	<Volt/Curr/Pow/Freq/PF>	<Tolerance>	<Calibration Value>

-4. 有効電力 力率 0<Power PF=0>

AC+DC	150V /200mA	150V, 200mA, 0W, 55Hz, LEAD 0	-0.030 W ~ 0.030 W	(0.000 W)
		150V, 200mA, 0W, 55Hz, LAG 0	-0.030 W ~ 0.030 W	(0.000 W)
	6V /20A	6V, 20A, 0W, 55Hz, LEAD 0	-0.12 W ~ 0.12 W	(0.01 W)
		6V, 20A, 0W, 55Hz, LAG 0	-0.12 W ~ 0.12 W	(-0.01 W)

SAMPLE

検査成績表

<TEST REPORT>

製造番号<Serial No.> (No. 260188888)
検査年月日<Test Date> (2026-01-27)
(<YYYY-MM-DD>)

項目	レクティ ファイア	レンジ	入力<Input> *2		許容範囲		校正値 *1	
<Item>	<Rect>	<Range>	<Curr>	<Freq>	<Tolerance>		<Calibration Value>	
-5. 外部センサ TYPE 1 CT比:100<External Sensor TYPE 1 CT Ratio:100>								
AC+DC	500A	500A	55Hz	499.00 A	~	501.00 A	(	499.99 A)
	200A	200A	55Hz	199.60 A	~	200.40 A	(	200.00 A)
	100A	100A	55Hz	99.80 A	~	100.20 A	(	100.00 A)
		50A	55Hz	49.90 A	~	50.10 A	(	50.00 A)
		1A	55Hz	0.90 A	~	1.10 A	(	1.00 A)
		0A	-	0.00 A	~	0.00 A	(	0.00 A)
DC	500A	500A		498.50 A	~	501.50 A	(	500.06 A)
		0A		0.00 A	~	0.00 A	(	0.00 A)
	200A	200A		199.40 A	~	200.60 A	(	200.05 A)
		0A		0.00 A	~	0.00 A	(	0.00 A)
	100A	100A		99.70 A	~	100.30 A	(	100.02 A)
		1A		0.80 A	~	1.20 A	(	1.00 A)
		0A		0.00 A	~	0.00 A	(	0.00 A)
	-100A		-100.30 A	~	-99.70 A	(	-100.03 A)	

項目	レクティ ファイア	レンジ	入力<Input> *2		許容範囲			校正値 *1	
<Item>	<Rect>	<Range>	<Curr>	<Freq>	<Tolerance>			<Calibration Value>	
-6. 外部センサ TYPE 2 CT比:10<External Sensor TYPE 2 CT Ratio:10>									
AC+DC		50A	50A	55Hz	49.900 A	~	50.100 A	(	50.000 A)
		20A	20A	55Hz	19.960 A	~	20.040 A	(	20.000 A)
		10A	10A	55Hz	9.980 A	~	10.020 A	(	10.000 A)
			5A	55Hz	4.990 A	~	5.010 A	(	4.999 A)
			0.1A	55Hz	0.090 A	~	0.110 A	(	0.100 A)
			0A	-	0.000 A	~	0.000 A	(	0.000 A)
DC		50A	50A		49.850 A	~	50.150 A	(	50.002 A)
			0A		0.000 A	~	0.000 A	(	0.000 A)
		20A	20A		19.940 A	~	20.060 A	(	20.002 A)
			0A		0.000 A	~	0.000 A	(	0.000 A)
		10A	10A		9.970 A	~	10.030 A	(	10.002 A)
			0.1A		0.080 A	~	0.120 A	(	0.100 A)
			0A		0.000 A	~	0.000 A	(	0.000 A)
		-10A		-10.030 A	~	-9.970 A	(	-10.002 A)	

SAMPLE

検査成績表

<TEST REPORT>

製造番号<Serial No.> (No. 260188888)
 検査年月日<Test Date> (2026-01-27)
 <YYYY-MM-DD>

項目 <Item>	レクティ ファイア <Rect>	レンジ <Range>	入力<Input> *2 <Volt/Curr/Pow/Freq/PF>	許容範囲 <Tolerance>	校正値 *1 <Calibration Value>
-7. 有効電力 力率 1 外部センサ TYPE 1 CT比: 100<Power PF=1 External Sensor TYPE 1 CT Ratio: 100>					
AC+DC		150V /200A	150V, 200A, 30kW, 55Hz, PF=1	29.940 kW ~ 30.060 kW	(30.013 kW)
			150V, 100A, 15kW, 55Hz, PF=1	14.970 kW ~ 15.030 kW	(15.007 kW)
			150V, 20A, 3kW, 55Hz, PF=1	2.967 kW ~ 3.033 kW	(3.001 kW)
		1000V /500A	1000V, 500A, 500kW, 55Hz, PF=1	499.00 kW ~ 501.00 kW	(500.13 kW)
		1000V /100A	1000V, 100A, 100kW, 55Hz, PF=1	99.80 kW ~ 100.20 kW	(100.05 kW)
		6V /500A	6V, 500A, 3kW, 55Hz, PF=1	2.9940 kW ~ 3.0060 kW	(3.0007 kW)
		6V /100A	6V, 100A, 600W, 55Hz, PF=1	598.80 W ~ 601.20 W	(600.25 W)
			6V(55Hz), 0A, 0W, -, -	-0.60 W ~ 0.60 W	(0.00 W)
DC		6V /100A	+6V, +100A, +600W	598.20 W ~ 601.80 W	(600.18 W)
			-6V, -100A, +600W	598.20 W ~ 601.80 W	(600.36 W)
			+6V, +20A, +120W	118.68 W ~ 121.32 W	(119.69 W)
			0V, 0A, 0W	-1.20 W ~ 1.20 W	(0.00 W)
		1000V /500A	+1000V, +500A, +500kW	498.50 kW ~ 501.50 kW	(500.39 kW)
			-1000V, -500A, +500kW	498.50 kW ~ 501.50 kW	(499.79 kW)

SAMPLE

検査成績表

<TEST REPORT>

製造番号<Serial No.> (No. 260188888)
 検査年月日<Test Date> (2026-01-27)
 <YYYY-MM-DD>

項目 <Item>	レクティ ファイア <Rect>	レンジ <Range>	入力<Input> *2 <Volt/Curr/Pow/Freq/PF>	許容範囲 <Tolerance>	校正値 *1 <Calibration Value>
-8. 有効電力 力率 1 外部センサ TYPE 2 CT比: 10<Power PF=1 External Sensor TYPE 2 CT Ratio: 10>					
AC+DC		150V /20A	150V, 20A, 3kW, 55Hz, PF=1	2.9940 kW ~ 3.0060 kW	(3.0005 kW)
			150V, 10A, 1.5kW, 55Hz, PF=1	1.4970 kW ~ 1.5030 kW	(1.5003 kW)
			150V, 0.5A, 0.075kW, 55Hz, PF=1	0.0720 kW ~ 0.0780 kW	(0.0750 kW)
		1000V /50A	1000V, 50A, 50kW, 55Hz, PF=1	49.900 kW ~ 50.100 kW	(50.008 kW)
		1000V /10A	1000V, 10A, 10kW, 55Hz, PF=1	9.980 kW ~ 10.020 kW	(10.002 kW)
		6V /50A	6V, 50A, 300W, 55Hz, PF=1	299.40 W ~ 300.60 W	(300.06 W)
		6V /10A	6V, 10A, 60W, 55Hz, PF=1	59.880 W ~ 60.120 W	(60.017 W)
			6V(55Hz), 0A, 0W, -, -	-0.060 W ~ 0.060 W	(0.000 W)
DC		6V /10A	+6V, +10A, +60W	59.820 W ~ 60.180 W	(60.023 W)
			-6V, -10A, +60W	59.820 W ~ 60.180 W	(60.005 W)
			+6V, +0.5A, +3W	2.877 W ~ 3.123 W	(2.975 W)
			0V, 0A, 0W	-0.120 W ~ 0.120 W	(0.000 W)
		1000V /50A	+1000V, +50A, +50kW	49.850 kW ~ 50.150 kW	(50.043 kW)
			-1000V, -50A, +50kW	49.850 kW ~ 50.150 kW	(49.969 kW)

SAMPLE

検査成績表

<TEST REPORT>

製造番号<Serial No.> (No. 260188888)
検査年月日<Test Date> (2026-01-27)
(<YYYY-MM-DD>)

項目 <Item>	レクティ ファイア <Rect>	レンジ <Range>	入力<Input> *2 <Volt/Curr/Pow/Freq/PF>	許容範囲 <Tolerance>	校正値 *1 <Calibration Value>
-9. 有効電力 力率 0 外部センサ TYPE 1 CT比:100<Power PF=0 External Sensor TYPE 1 CT Ratio:100>					
AC+DC		150V /200A	150V, 200A, 0W, 55Hz, LEAD 0	-0.045 kW ~ 0.045 kW	(0.000 kW)
			150V, 200A, 0W, 55Hz, LAG 0	-0.045 kW ~ 0.045 kW	(0.000 kW)
		6V /500A	6V, 500A, 0W, 55Hz, LEAD 0	-0.0045 kW ~ 0.0045 kW	(0.0000 kW)
			6V, 500A, 0W, 55Hz, LAG 0	-0.0045 kW ~ 0.0045 kW	(0.0000 kW)

項目 <Item>	レクティ ファイア <Rect>	レンジ <Range>	入力<Input> *2 <Volt/Curr/Pow/Freq/PF>	許容範囲 <Tolerance>	校正値 *1 <Calibration Value>
-10. 有効電力 力率 0 外部センサ TYPE 2 CT比:10<Power PF=0 External Sensor TYPE 2 CT Ratio:10>					
AC+DC		150V /20A	150V, 20A, 0W, 55Hz, LEAD 0	-0.0045 kW ~ 0.0045 kW	(0.0000 kW)
			150V, 20A, 0W, 55Hz, LAG 0	-0.0045 kW ~ 0.0045 kW	(0.0000 kW)
		6V /50A	6V, 50A, 0W, 55Hz, LEAD 0	-0.45 W ~ 0.45 W	(0.01 W)
			6V, 50A, 0W, 55Hz, LAG 0	-0.45 W ~ 0.45 W	(-0.01 W)

2. ピーク値測定<Peak Measurement>

項目 <Item>	レクティ ファイア <Rect>	レンジ <Range>	入力<Input> <Volt/Curr> <Freq>	許容範囲 **A <Tolerance>	校正値 *1, **A <Calibration Value>
-1. 電圧<Voltage>					
AC+DC		3.6kV	600V 55Hz	±(0.7766 kV ~ 0.9205 kV)	(-0.8488 kV)
-2. 電流<Current>					
AC+DC		60A	10A 55Hz	±(12.943 A ~ 15.342 A)	(-14.162 A)
-3. 外部センサ TYPE 1 CT比:100<External Sensor TYPE 1 CT Ratio:100>					
AC+DC		3kA	500A *2 55Hz	±(0.6472 kA ~ 0.7671 kA)	(-0.7074 kA)
-4. 外部センサ TYPE 2 CT比:10<External Sensor TYPE 2 CT Ratio:10>					
AC+DC		60A	10A *2 55Hz	±(12.943 A ~ 15.342 A)	(-14.150 A)

**A. 判定は校正値と同じ符号の許容範囲を用いて行っています。

<The decision depends on the tolerance range of the sign same as the calibration value.>

SAMPLE

検査成績表

<TEST REPORT>

製造番号<Serial No.> (No. 260188888)
検査年月日<Test Date> (2026-01-27)
(<YYYY-MM-DD>)

3. 周波数特性<Frequency Characteristic>

項目	レクティ ファイア	ゼロ クロス フィルタ	レンジ	入力<Input>		許容範囲			校正値 *1	
<Item>	<Rect>	<Filter>	<Range>	<Volt/Curr/ Pow/PF>	<Freq>	<Tolerance>			<Calibration Value>	
-1. 電圧<Voltage>										
	AC+DC	100Hz	6V	6V	10Hz	5.9820 V	～	6.0180 V	(	5.9985 V)
					16Hz	5.9880 V	～	6.0120 V	(	5.9991 V)
					50Hz	5.9910 V	～	6.0090 V	(	5.9993 V)
					60Hz	5.9910 V	～	6.0090 V	(	5.9994 V)
		500Hz			500Hz	5.9880 V	～	6.0120 V	(	5.9991 V)
		100kHz			10kHz	5.9820 V	～	6.0180 V	(	5.9978 V)
					50kHz	5.9520 V	～	6.0480 V	(	6.0071 V)
					100kHz	5.8560 V	～	6.1440 V	(	6.0263 V)
-2. 電流<Current>										
	AC+DC	100Hz	200mA	200mA	10Hz	199.40 mA	～	200.60 mA	(	200.04 mA)
					16Hz	199.60 mA	～	200.40 mA	(	200.04 mA)
					50Hz	199.70 mA	～	200.30 mA	(	200.07 mA)
					60Hz	199.70 mA	～	200.30 mA	(	200.08 mA)
		500Hz			500Hz	199.60 mA	～	200.40 mA	(	200.02 mA)
		5kHz			1kHz	199.40 mA	～	200.60 mA	(	200.04 mA)
		100kHz			10kHz	198.14 mA	～	201.86 mA	(	200.51 mA)
					100kHz	186.80 mA	～	213.20 mA	(	198.67 mA)
-3. 有効電力<Power>										
	AC+DC	100Hz	6V /200mA	6V, 200mA, 1.2W, PF=1	10Hz	1.1964 W	～	1.2036 W	(	1.2002 W)
					16Hz	1.1976 W	～	1.2024 W	(	1.2002 W)
					50Hz	1.1982 W	～	1.2018 W	(	1.2005 W)
					60Hz	1.1982 W	～	1.2018 W	(	1.2003 W)
		500Hz			500Hz	1.1976 W	～	1.2024 W	(	1.2003 W)
		5kHz			1kHz	1.1964 W	～	1.2036 W	(	1.2003 W)
		100kHz			10kHz	1.1889 W	～	1.2111 W	(	1.2020 W)
					30kHz	1.1640 W	～	1.2360 W	(	1.2080 W)
-4. 外部センサ TYPE 1 CT比:100<External Sensor TYPE 1 CT Ratio:100>										
	AC+DC	100Hz	200A	200A *2	10Hz	199.40 A	～	200.60 A	(	199.97 A)
					16Hz	199.40 A	～	200.60 A	(	199.99 A)
					50Hz	199.60 A	～	200.40 A	(	200.00 A)
					60Hz	199.60 A	～	200.40 A	(	200.00 A)
		500Hz			500Hz	199.40 A	～	200.60 A	(	200.00 A)
		5kHz			1kHz	199.40 A	～	200.60 A	(	199.98 A)
		100kHz			10kHz	198.14 A	～	201.86 A	(	199.96 A)
					100kHz	190.80 A	～	209.20 A	(	197.85 A)
-5. 外部センサ TYPE 2 CT比:10<External Sensor TYPE 2 CT Ratio:10>										
	AC+DC	100Hz	10A	10A *2	10Hz	9.970 A	～	10.030 A	(	9.998 A)
					16Hz	9.970 A	～	10.030 A	(	9.998 A)
					50Hz	9.980 A	～	10.020 A	(	9.999 A)
					60Hz	9.980 A	～	10.020 A	(	9.999 A)
		500Hz			500Hz	9.970 A	～	10.030 A	(	9.999 A)
		5kHz			1kHz	9.970 A	～	10.030 A	(	9.998 A)
		100kHz			10kHz	9.907 A	～	10.093 A	(	9.998 A)
					100kHz	9.540 A	～	10.460 A	(	9.896 A)

SAMPLE

検査成績表

<TEST REPORT>

製造番号<Serial No.> (No. 260188888)
検査年月日<Test Date> (2026-01-27)
(<YYYY-MM-DD>)

項目	レクティ ファイア	ゼロ クロス フィルタ	レンジ	入力<Input> *2		許容範囲			校正値 *1		
<Item>	<Rect>	<Filter>	<Range>	<Volt/Curr/ Pow/PF>	<Freq>	<Tolerance>			<Calibration Value>		
-6. 有効電力 外部センサ TYPE 1 CT比:100<Power External Sensor TYPE 1 CT Ratio:100>											
	AC+DC	100Hz	6V/200A	6V, 200A, 1.2kW, PF=1	10Hz	1.1964 kW	～	1.2036 kW	(	1.2001 kW)	
					16Hz	1.1964 kW	～	1.2036 kW	(	1.2005 kW)	
					50Hz	1.1976 kW	～	1.2024 kW	(	1.2005 kW)	
					60Hz	1.1976 kW	～	1.2024 kW	(	1.2006 kW)	
		500Hz			500Hz	1.1964 kW	～	1.2036 kW	(	1.2005 kW)	
		5kHz			1kHz	1.1964 kW	～	1.2036 kW	(	1.2004 kW)	
		100kHz			10kHz	1.1889 kW	～	1.2111 kW	(	1.1998 kW)	
					30kHz	1.1712 kW	～	1.2288 kW	(	1.1975 kW)	
-7. 有効電力 外部センサ TYPE 2 CT比:10<Power External Sensor TYPE 2 CT Ratio:10>											
	AC+DC	100Hz	6V /10A	6V, 10A, 60W, PF=1	10Hz	59.820 W	～	60.180 W	(	60.006 W)	
					16Hz	59.820 W	～	60.180 W	(	60.013 W)	
					50Hz	59.880 W	～	60.120 W	(	60.013 W)	
					60Hz	59.880 W	～	60.120 W	(	60.015 W)	
		500Hz			500Hz	59.820 W	～	60.180 W	(	60.010 W)	
		5kHz			1kHz	59.820 W	～	60.180 W	(	60.004 W)	
		100kHz			10kHz	59.442 W	～	60.558 W	(	59.987 W)	
					30kHz	58.560 W	～	61.440 W	(	59.953 W)	

4. 周波数測定<Frequency Measurement>

項目	レクティ ファイア	ゼロ クロス フィルタ	レンジ	入力<Input>		許容範囲		校正値 *1	
<Item>	<Rect>	<Filter>	<Range>	<Volt/Curr>	<Freq>	<Tolerance>		<Calibration Value>	
-1. 電圧, 電流<Voltage, Current>									
	AC+DC	100Hz	6V /1mA	6V, 0A	55Hz	54.944 Hz	~	55.056 Hz	(55.000 Hz)
				0V, 1mA	55Hz	54.889 Hz	~	55.111 Hz	(55.000 Hz)
-2. 外部センサ TYPE 1 CT比:100<External Sensor TYPE 1 CT Ratio:100>									
	AC+DC	100Hz	100A	100A *2	55Hz	54.944 Hz	~	55.056 Hz	(55.000 Hz)
-3. 外部センサ TYPE 2 CT比:10<External Sensor TYPE 2 CT Ratio:10>									
	AC+DC	100Hz	10A	10A *2	55Hz	54.944 Hz	~	55.056 Hz	(55.001 Hz)