

Multiple Output Linear D.C. Power Supply



GPE-X323 Series

FEATURES

- 1/2/3/4 Independent Isolated Output
- 4.3 Inch LCD Display
- Setting & Read Back Resolution 10mA/1mA
- Output On/off
- Analog Control (Remote I/O) For Output ON/OFF
- Set View Function For Checking an Original V/I Setting During Output On
- Key Lock Function
- Tracking Series And Parallel Operation
- Smart Cooling Fan Achieving Low Noise
- Optional European Jack Type Terminal

The GPE-X323 series is cutting edge, economical linear DC Power supplies. The GPE-X323 series features output power from 192 to 217 watts, three independent isolated output channels (for GPE-3323), high resolution, low noise, high reliability, and compact size. The GPE-X323 series has a built-in digital panel control design to replace conventional control method. This unique design allows the GPE-X323 series linear DC power supply to provide users with more efficient functionalities, including set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage and current parameters. Additionally, output key light facilitates users in clearly reading the operational status of power supply.

High Resolution


The GPE-X323 series features 10mV/1mA high resolution (for setting and read back). The series outputs a pure and stable power supply. Users can easily simulate small voltage or small current measurements for DUTs that is the area the conventional low resolution linear power supplies can't achieve.



4.3 Inch LCD display provide high resolution for 10mV/1mA

Tracking Series and Parallel Operation

In addition to independent output channels, the GPE-X323 series provides tracking series and parallel operation (For GPE-2323/GPE-3323/GPE-4323). The series and parallel connections allow power supplies to output 32V/6A (Parallel Connection) and 64V/3A (Series Connection).



Internal connection for tracking Series and Parallel operation via control panel

Convenient Function


The GPE-X323 series has a built-in set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage/current parameters.



The key lock function prevent DUTs from unnecessary damages caused by mis-operation.

Remote I/O for output On/Off function

The GPE-X323 Series also provides the analog control (Remote I/O) function for external output On/Off control.



For controlling the output On/Off function through the specific pin assignment of remote control connector which is in rear panel.



Front



Rear Panel

APPLICATIONS

- Laboratories and Educational Facilities
- Product Testing and Quality Assurance
- Service Operation and Post-Sales Support
- Product Development and Debugging

SPECIFICATIONS

		GPE-4323				GPE-3323			GPE-2323		GPE-1326
OUTPUT MODE	Number of Channel Voltage Current Tracking Series Voltage Tracking Parallel Current	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2	CH1
		0~32V	0~32V	0~5V	0~15V	0~32V	0~32V	5V	0~32V	0~32V	0~32V
		0~3A	0~3A	0~1A	0~1A	0~3A	0~3A	5A	0~3A	0~3A	0~6A
		0~64V		-		0~64V		-		0~64V	
		0~6A		-		0~6A		-		-	
CONSTANT VOLTAGE OPERATION	Line Regulation Load Regulation Ripple & Noise Recovery Time	$\leq 0.01\%+3mV$ $\leq 0.01\%+3mV$ (rating current $\leq 3A$); $\leq 0.02\%+5mV$ (rating current $> 3A$) $\leq 1mVrms$ (5Hz~1MHz) $\leq 100\mu s$ (50% Load Change, minimum load 0.5A)									
CONSTANT CURRENT OPERATION	Line Regulation Load Regulation Ripple & Noise	$\leq 0.2\%+3mA$ $\leq 0.2\%+3mA$ $\leq 3mA_{rms}$									
TRACKING OPERATION (CH1,CH2)	Tracking Error Parallel Regulation Series Regulation Ripple & Noise	$\leq 0.1\%+10mV$ of Master(0~32V) No Load , with Load add load regulation $\leq 100mV$ Line : $\leq 0.01\%+3mV$ Load : $\leq 0.01\%+3mV$ (rating current $\leq 3A$); $\leq 0.02\%+5mV$ (rating current $> 3A$) Line : $\leq 0.01\%+5mV$ Load : $\leq 100mV$									
CH3 OPERATION FOR (GPE-3323)	Output Voltage Output Current Line Regulation Load Regulation Ripple & Noise	5.0V, $\pm 5\%$ 5A $\leq 3mV$ $\leq 5mV$ 1mVrms(5Hz~1MHz)									
METER	Voltage Resolution Current Resolution Setting Accuracy Readback Accuracy	10mV 1mA Voltage \pm (0.1% of reading +30mV); Current \pm (0.3% of reading +6mA) Voltage \pm (0.1% of reading +30mV); Current \pm (0.3% of reading +6mA)									
INSULATION	Chassis and Terminal Chassis and AC Cord	20M Ω or above (DC 500V) 30M Ω or above (DC 500V)									
ENVIRONMENT CONDITION	Operation Temp Storage Temp Operating Humidity Storage Humidity	0~40 $^{\circ}C$ -10~70 $^{\circ}C$ $\leq 80\%$ RH $\leq 70\%$ RH									
OTHER	Power Source Dimensions & Weight	AC100V/120V/220V $\pm 10\%$; 230V(+10%~-6%); 50/60Hz 210(W)x 155(H) x 306(D) mm ; Approx. 7kg									

Specifications subject to change without notice.

PE-x303CD1DH

ORDERING INFORMATION

GPE-1326 Single Channel, 192W Linear DC Power Supply
GPE-2323 2 Channels, 192W Linear DC Power Supply
GPE-3323 3 Channels, 217W Linear DC Power Supply
GPE-4323 4 Channels, 212W Linear DC Power Supply

ACCESSORIES

User Manual (CD) x 1 ; Power Cord x 1
GPE-1326 Test Lead GTL-104 x 1 ; GTL-105 x 1 ; or European GTL-204A x 1, GTL-203A x1
GPE-2323 Test Lead GTL-104 x 2 ; or European GTL-204A x 2,
GPE-3323 Test Lead GTL-104 x 3 ; or European GTL-204A x 3
GPE-4323 Test Lead GTL-104 x 2 ; GTL-105 x 2 or European GTL-204A x 2 , GTL-203A x 2

Global Headquarters

GOOD WILL INSTRUMENT CO., LTD.

No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan
 T +886-2-2268-0389 F +886-2-2268-0639
 E-mail: marketing@goodwill.com.tw

China Subsidiary

GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.

No. 521, Zhujiang Road, Snd, Suzhou Jiangsu 215011 China
 T +86-512-6661-7177 F +86-512-6661-7277
 E-mail: marketing@instek.com.cn

Malaysia Subsidiary

GOOD WILL INSTRUMENT (M) SDN. BHD.

27, Persiaran Mahsuri 1/1, Sunway Tunas,
 11900 Bayan Lepas, Penang, Malaysia
 T +604-6309988 F +604-6309989
 E-mail: sales@goodwill.com.my

Europe Subsidiary

GOOD WILL INSTRUMENT EURO B.V.

De Run 5427A, 5504DG Veldhoven, THE NETHERLANDS
 T +31(0)40-2557790 F +31(0)40-2541194

U.S.A. Subsidiary

INSTEK AMERICA CORP.

5198 Brooks Street Montclair, CA 91763, U.S.A.
 T +1-909-399-3535 F +1-909-399-0819
 E-mail: sales@instekamerica.com

Japan Subsidiary

TEXIO TECHNOLOGY CORPORATION.

7F Towata Fudosan Shin Yokohama Bldg., 2-18-13 Shin
 Yokohama, Kohoku-ku, Yokohama, Kanagawa,
 222-0033 Japan
 T +81-45-620-2305 F +81-45-534-7181
 E-mail: info@texio.co.jp

Korea Subsidiary

GOOD WILL INSTRUMENT KOREA CO., LTD.

#1406, Ace Hightech-City B/D 1Dong,
 Mullaee-Dong 3Ga 55-20, Yeongduengpo-Gu, Seoul, Korea
 T +82-2-3439-2205 F +82-2-3439-2207
 E-mail: gwinstek@gwinstek.co.kr

GW INSTEK

Simply Reliable



www.gwinstek.com

www.facebook.com/GWInstek