Keysight Power Dividers







11636B power divider

87302C Hybrid power dividers

11636C power divider

The Keysight Technologies, Inc. power dividers are an RF and microwave accessory construct by equivalent resistance of 50 Ω , it's used to divide power equally in a uniform transmission line for comparison measurements. The power divider provides a good impedance match at both the output arms when the input is terminated in the system characteristic impedance (50 Ω). Once a good source match has been achieved, the power divider may be used to divide the output into equal signals for comparison measurements.

Key measurements

- Broad operating frequency range up to 50 GHz eliminates the need for multiple dividers
- Excellent amplitude (±0.3 dB) and phase tracking (±2°) ensures highly accurate power division
- Low SWR 1.67 at 50 GHz minimizes measurement uncertainty



Product specifications

| Model | Frequency | Max SWR | Maximum insertion loss (dB) | Minimum isolation (dB) | Maximum amplitude tracking (dB) ¹ | Maximum phase tracking (°) 1 |
|--------|----------------|---------|-----------------------------|------------------------|--|------------------------------|
| 11636A | DC to 18 GHz | 1.35 | 6.0 typ ² | - | 0.5 3 | ±2° typ |
| 11636B | DC to 26.5 GHz | 1.29 | 7.5 | - | 0.25 ³ | ±2° typ |
| 11636C | DC to 50 GHz | 1.67 | 8.5 | - | 0.30 4 | ±2° |
| 87302C | 0.5 to 18 GHz | 1.45 | 1.5 ⁵ | 19 | 0.3 | 6 |
| | 18 to 26.5 GHz | 1.6 | 1.9 5 | 19 | 0.5 | 10 |
| 87303C | 1.0 to 18 GHz | 1.45 | 1.2 5 | 19 | 0.3 | 6 |
| | 18 to 26.5 GHz | 1.6 | 1.6 ⁵ | 21 | 0.5 | 10 |
| 87304C | 2.0 to 18 GHz | 1.45 | 1.1 5 | 19 | 0.3 | 6 |
| | 18 to 26.5 GHz | 1.6 | 1.4 5 | 18 | 0.5 | 10 |

^{1.} Amplitude and phase tracking are the ratio of one output to the other in dB or degrees, respectively.

For more detail information on "Agilent Power Divider", please refer to product literature number 5989-6698EN.

Download or order from www.keysight.com/find/mta
To find a distributor in your area, go to: www.keysight.com/find/distributors

KEYSIGHT SERVICES

Accelerate Technology Adoption. Lower costs.

www.keysight.com/find/services

Keysight Services helps you improve productivity and product quality with our comprehensive service offerings of one-stop calibration, repair, asset management, technology refresh, consulting, training, and more.



^{2. 5.8} to 7.2 dB up to 10 GHz; 5.8 to 7.5 dB up to 18 GHz.

^{3.} At 18 GHz.

^{4.} At 50 GHz.

^{5.} Insertion loss is in addition to 3 dB coupling loss.