

PS30 Switching DC Power Supply

Adjustable 0 to 30V with 1A fixed output

Features:

- Dual 3-Digit LCD displays for voltage and current
- Output accuracy: $\pm (0.5\% + 2 \text{ digits})$
- Current overload protection
- Low ripple and noise
- Includes AC power cord and (2) spare fuses

Applications:

Testing and Repair of circuit boards, vocational school/technical school/college level electronics classroom education, field service, and hobbyists



Specifications

Output Voltage	0 to 30.00V
Output Current	1A
Output Power	30W
Load Regulation	100mV
Line Regulation	15mV
Ripple and noise	70mVrms
Display	Dual 3-Digit LCD (voltage and current)
Power	85 to 265VAC, 50/60Hz
Dimensions / Weight	4.3 x 3 x 5.5" (110 x 74 x 140mm) / 10.6oz (300g)

Ordering Information:

PS30 Switching DC Power Supply

