

Tripp Lite
1111 W. 35th Street

Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

# OmniVS 120V 1000VA 500W Line-Interactive UPS, Tower, USB port

#### MODEL NUMBER: OMNIVS1000











#### **Highlights**

- 1000VA / 1kVA tower 120V line interactive UPS
- Corrects brownouts as low as 89V without using battery power
- 6 UPS battery supported outlets, 2 surge-only outlets
- USB port, TEL/DSL/ethernet protection
- NEMA 5-15P input plug and 8 NEMA 5-15R outlets

### **Package Includes**

- OMNIVS1000 Line Interactive UPS
- USB and telephone cable
- User manual with warranty information

#### Description

Tripp Lite's OMNIVS1000 line interactive UPS system offers voltage regulation, surge suppression and long lasting battery support for personal computers, internetworking equipment and other sensitive electronics. Internal UPS circuits support entry level PC systems for up to 60 minutes during power failures so that connected equipment can be shut down without data loss. Automatic Voltage Regulation (AVR) circuits regulate brownouts as low as 89 volts back to usable levels without using battery power. Offers complete desktop power protection in an attractive black tower configuration. Includes 6 battery supported outlets for computer, monitor and one vital system peripheral, plus 2 additional surge suppression-only outlets for printers and other system accessories not requiring battery support. USB port enables optional unattended system shutdown without data loss in the case of extended power failure. USB cable included. PowerAlert software available via free download. Built-in RJ45 TEL/Ethernet suppression jacks protect modem, fax machine, cordless phone or other peripheral with a standard singleline tel/DSL or data line connection. Built-in audible alarm and 4 front panel LEDs indicate line power status, battery power status, battery low/replace status and overload. 1000VA/500 watt power handling ability supports entry-level PCs, network workstations, point-of-sale equipment, small business phone systems, audio/video equipment and home theater systems. Offers 3.5 minutes battery runtime with a full load of 1000VA/500 watts and 14 minutes with a half load of 500VA/250 watts. Supports battery replacement via built-in access panel. \$200,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only).

#### **Features**

- OMNIVS1000 Uninterruptible Power Supply offers voltage regulation, surge suppression and long lasting battery support
- · Supports entry level PCs up to 60 minutes during blackouts to enable shutdown without data loss
- Regulates brownouts as low as 89 volts back to usable levels without using battery power
- 6 UPS battery supported outlets, plus 2 additional surge suppression-only outlets
- USB port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert
- HID-compliant USB port also enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Built-in RJ45 TEL/Ethernet suppression jacks protect modem, fax machine, cordless phone or other peripheral with a standard single-line tel/DSL or data line connection
- Audible alarm and 4 front panel LEDs offer complete UPS and line power status information



- 1000VA/500 watt power handling ability supports a variety of sensitive electronic equipment
- 3.5 minutes full load runtime (1000VA/500 watts), 14 minutes half load runtime (500VA/250 watts)
- Supports battery replacement via built-in access panel
- Optional PDUB15 bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment
- Short circuit protection in AC and battery mode
- \$200,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only)

## **Specifications**

OVERVIEW		
UPC Code	037332119728	
UPS Type	Line-Interactive	
INPUT		
Rated input current (Maximum Load)	12A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P	
UPS Input Cord Length (ft.)	6	
UPS Input Cord Length (m)	1.8	
Recommended Electrical Service	15A 120V	
Input Phase	Single-Phase	
оитрит		
Output Volt Amp Capacity (VA)	1000	
Output Capacity (kVA)	1	
Output Watt Capacity (Watts)	500	
Nominal Voltage Details	115v nominal output in battery mode	
Frequency Compatibility	60 Hz	
Output Voltage Regulation (Battery Mode)	+/- 5%	
UPS Output Receptacles (Surge Suppression Only)	6 UPS outlets, 2 surge-only outlets	
Hot-Swap PDU options	PDUB15 (2U / 8 5-15R outlets)	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	PWM sine wave	
Nominal Output Voltage(s) Supported	110V; 115V; 120V	





Outsid Brooks los		
Output Receptacles	(8) 5-15R	
Individually Controllable Load Banks	No	
BATTERY		
Battery Type	Valve Regulated Lead Acid (VRLA)	
Full Load Runtime (min.)	3.5 min. (500w)	
Half Load Runtime (min.)	14 min. (250w)	
Expandable Runtime	No	
DC System Voltage (VDC)	12	
Battery Recharge Rate (Included Batteries)	Less than 4.5 hours from 10% to 90%	
Battery Access	Battery access door	
Internal UPS Replacement Battery Cartridge	<a class="productLink" href="//www.tripplite.com/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Belkin-Best-Powerware-Liebert-other-UPS~RBC51">RBC51</a> /a>	
Battery Replacement Description	Hot-swappable, user replaceable batteries	
VOLTAGE REGULATION		
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with input voltage as low as 89	
Undervoltage Correction	Input voltages between 89 and 105 are boosted by 14%	
USER INTERFACE, ALERTS & CONTROLS		
USER INTERFACE, ALERTS & CON	TROLS	
USER INTERFACE, ALERTS & CON Switches	TROLS  2 Switches control off/on power status and alarm-cancel/self-test operation	
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-	
Switches Alarm Cancel Operation	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status	
Switches  Alarm Cancel Operation  Audible Alarm	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions	
Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions	
Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators  SURGE / NOISE SUPPRESSION	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions  4 LEDs indicate line power, battery power, overload and battery low/replace status	
Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions  4 LEDs indicate line power, battery power, overload and battery low/replace status	
Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response Time	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions  4 LEDs indicate line power, battery power, overload and battery low/replace status  510  Instantaneous	
Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response Time  UPS Dataline Suppression	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions  4 LEDs indicate line power, battery power, overload and battery low/replace status  510  Instantaneous  1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet	
Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response Time  UPS Dataline Suppression  EMI / RFI AC Noise Suppression	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions  4 LEDs indicate line power, battery power, overload and battery low/replace status  510  Instantaneous  1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet	
Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response Time  UPS Dataline Suppression  EMI / RFI AC Noise Suppression	2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions  4 LEDs indicate line power, battery power, overload and battery low/replace status  510  Instantaneous  1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet  Yes	





Primary UPS Depth (mm)	191
Primary UPS Height (mm)	274
Primary UPS Width (mm)	132
Shipping Dimensions (hwd / cm)	25.40 x 35.31 x 19.81
Shipping Dimensions (hwd / in.)	10.00 x 13.90 x 7.80
Shipping Weight (kg)	7.64
Shipping Weight (lbs.)	16.85
UPS Housing Material	PVC
UPS Power Module Dimensions (hwd, cm)	27.43 x 13.21 x 19.05
UPS Power Module Dimensions (hwd, in.)	10.8 x 5.2 x 7.5
UPS Power Module Weight (kg)	8.35
UPS Power Module Weight (lbs.)	18.4
ENVIRONMENTAL	
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Relative Humidity	0 to 95%, non-condensing
AC Mode BTU / Hr. (Full Load)	24
Battery Mode BTU / Hr. (Full Load)	664
AC Mode Efficiency Rating (100% Load)	96%
COMMUNICATIONS	
PowerAlert Software	For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at https://www.tripplite.com/poweralert
Communications Cable	USB interface cable included
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
Network UPS Tools Compatibility	NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite
Network Management Card Description	Network management not supported
Communications Interface	USB (HID enabled)
LINE / BATTERY TRANSFER	
Transfer Time	4 milliseconds
Low Voltage Transfer to Battery Power (Setpoint)	89
High Voltage Transfer to Battery Power (Setpoint)	139





FEATURES & SPECIFICATIONS	
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported
High Availability UPS Features	Automatic Voltage Regulation (AVR); Hot swappable batteries; Surge/noise protection
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS
STANDARDS & COMPLIANCE	
Product Certifications	CSA (Canada); NOM (Mexico); UL 1778
Product Compliance	RoHS; FCC Part 15 Class B (USA)
WARRANTY	
Product Warranty Period (U.S. & Canada)	3-year limited warranty
Product Warranty Period (Latin America)	3-year limited warranty
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	3-year limited warranty
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$200,000 <a class="insuranceLink" href="//www.tripplite.com/support/insurance-policy">Ultimate Lifetime Insurance</a>

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <a href="https://www.tripplite.com/products/product-certification-agencies">https://www.tripplite.com/products/product-certification-agencies</a>