



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

## 3.8kW Single-Phase Monitored Automatic Transfer Switch PDU, 2 200-240V 16A L6-20P Inputs, 1 L6-20R Outlet, 1U

MODEL NUMBER: PDUMNH20HVAT



High-capacity 3.3/3.8kW PDU with ATS provides remote power monitoring and enables redundant power for non-redundant hardware. Digital display and Ethernet interface monitor load levels to prevent overloads that cause downtime.

### Description

The PDUMNH20HVAT 3.3/3.8kW Single-Phase 200-240V Monitored Automatic Transfer Switch / ATS PDU provides remote power monitoring and enables redundant power for network devices with non-redundant power supply configurations. Ideal for data centers and server rooms, it mounts in 1U of space in EIA-standard 19-inch racks and features one L6-20R outlet—perfect for connecting a single device or a 0U 208/240V PDU with an L6-20P plug.

Dual 10-ft. (3.05 m) input cords with L6-20P plugs connect to separate primary and secondary single-phase power sources. The PDU constantly evaluates the power quality of both input sources. Dynamic solid-state (TRIAC) automatic transfer switching allows the PDU to switch to the secondary source within 1–5 milliseconds should the primary source fail or become unstable to ensure your connected equipment operates without interruption.

The built-in Java-free HTML5-based LX Platform network interface enables full remote access for PDU status monitoring and email notifications via secure web browser, SNMP, telnet or SSH. It supports 10/100 Mbps auto-sensing for optimum communication with an Ethernet network. Optional EnviroSense2 modules (sold separate) provide a variety of environmental monitoring capabilities, including temperature and humidity conditions. Protocols supported include IPv4, IPv6, HTTP, HTTPS, SMTP, SNMPv1, SNMPv2, SNMPv3, telnet, SSH, FTP, DHCP and NTP. DHCP/Manual configuration lets you assign network settings to the card automatically, reducing the need for manual configuration. Automated alerts help prevent accidental overloads, power loss and downtime.

### Features

**Primary and Secondary Inputs for Power Redundancy** Provides remote power monitoring and enables redundant power for network devices with non-redundant power supply configurations  
Dual 10-ft. (3.05 m) input cords with L6-20P plugs connect to separate primary and secondary single-phase power sources  
Fault-tolerant, hot-swappable UPS protection when used with single UPS; fully redundant UPS protection when each cord is connected to separate UPS systems

**Built-In L6-20R Outlet** Connects a single device or indirectly powers equipment through a 0U 200-240V PDU with L6-20P input (sold separately)

**Automatic Transfer Switching (ATS)** Dynamic solid-state (TRIAC) automatic transfer switching  
Switches to secondary power source if primary source fails or becomes unstable  
1-5 ms transfer time ensures

### Highlights

- Two single-phase L6-20P inputs with 10-ft. (3.05 m) cords
- L6-20R outlet for connecting single device or 0U vertical PDU
- Automatic transfer switching within 1-5 ms
- Built-in LX Platform Interface for remote access
- Digital display for real-time status monitoring

### Package Includes

- PDUMNH20HVAT 3.3/3.8kW Single-Phase 200-240V ATS/Monitored PDU
- Mounting brackets
- Owner's manual



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

uninterrupted operation of connected equipment Built-in processor prevents switching if secondary source is unavailable or of lower quality than primary source

**Multifunction Digital Display** Reports source A and source B input power status and other information, including power availability, line voltage, frequency, amps, kilowatts and power factor

**Advanced Network Monitoring** LX Platform interface allows full remote access for power monitoring with email notifications via secure web browser, SNMP, telnet or SSH Real-time load/current data with billing-grade accuracy (+/- 1 percent) Automated alerts help prevent overloads, power loss and downtime Optional EnviroSense2 modules (sold separately) provide a variety of environmental monitoring capabilities

**Broad Communications Compatibility** 10/100 Mbps auto-sensing allows optimal communication with 10/100 Base-T networks

**Mounts Horizontally in 1U of Rack Space** Compatible with EIA-standard 19 in. 4-post racks and rack enclosures Optional PDU4PKIT rail kit (sold separately) adds rear mounting support

## Specifications

| OVERVIEW                          |  |
|-----------------------------------|--|
| UPC Code                          | 037332187932   |
| PDU Type                          | Monitored; Auto-Transfer Switch  |
| INPUT                             |  |
| PDU Input Voltage                 | 200; 208; 220; 230; 240  |
| Recommended Electrical Service    | Two single-phase 16/20A 200-240V circuits  |
| Maximum Input Amps                | 16   |
| Maximum Input Amps Details        | Agency de-rated to 16A continuous  |
| PDU Plug Type                     | (2) NEMA L6-20P  |
| Input Phase                       | Single-Phase   |
| Input Cord Details                | Set of two inputs connect to separate PRIMARY and SECONDARY power sources                |
| Input Cord Length (ft.)           | 10   |
| Input Cord Length (m)             | 3.05   |
| OUTPUT                            |  |
| Output Capacity Details           | 3.8kW (240V), 3.7kW (230V), 3.5kW (220V), 3.3kW (208V), 3.2kW (200V); 16A total capacity |
| Frequency Compatibility           | 50 / 60 Hz   |
| Output Receptacle Details         | Output receptacle is on a 61cm / 24 inch cordset   |
| Output Receptacles                | (1) L6-20R   |
| Output Nominal Voltage            | 200-240V   |
| USER INTERFACE, ALERTS & CONTROLS |  |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

|                                      |  |
|--------------------------------------|--|
| Front Panel LCD Display              | Digital display reports input current in amps (Source A, Source B), output kilowatts (total), input voltage (Source A, Source B), input frequency (Source A, Source B) and output power factor                                       |
| Front Panel LEDs                     | Front panel LEDs confirm amp (A) / kilowatt (kW) / voltage (V) / frequency (Hz) and power factor (PF) reporting information; Additional set of LEDs indicate Source A and Source B inputs for preferred, available and in-use status |
| Switches                             | ENTER and MODE switches toggle the digital display to display all reported information   |
| Current Measurement Accuracy (Amps)  | +/-1%  |
| Voltage Measurement Accuracy (Volts) | +/-1%  |
| Power Measurement Accuracy (Watts)   | +/-1%  |
| <b>SURGE / NOISE SUPPRESSION</b>     |  |
| Automatic Shut-Off                   | No   |
| <b>PHYSICAL</b>                      |  |
| Material of Construction             | Metal  |
| Form Factors Supported               | 1U rackmount   |
| Minimum Required Rack Depth (cm)     | 44.45  |
| Minimum Required Rack Depth (inches) | 17.5   |
| PDU Form Factor                      | Horizontal (1U)  |
| Shipping Dimensions (hwd / cm)       | 18.29 x 52.07 x 52.07  |
| Shipping Dimensions (hwd / in.)      | 7.20 x 20.50 x 20.50   |
| Shipping Weight (kg)                 | 7.21   |
| Shipping Weight (lbs.)               | 15.90  |
| Unit Dimensions (hwd / in.)          | 1.72 x 16.93 x 14  |
| Unit Dimensions (hwd / cm)           | 4.4 x 43 x 35.6  |
| Unit Weight (lbs.)                   | 15.37  |
| Unit Weight (kg)                     | 6.97   |
| <b>ENVIRONMENTAL</b>                 |  |
| Operating Temperature Range          | 0C ~ 40C (32F ~ 104F)  |
| Storage Temperature Range            | -30°C to +50°C (-22°F to +122°F)   |
| Relative Humidity                    | 5-95% non-condensing   |
| Operating Elevation (ft.)            | 0-10,000   |
| Operating Elevation (m)              | 0-3000   |
| <b>COMMUNICATIONS</b>                |  |
| PowerAlert Software                  | LX Platform Interface: PowerAlert Device Manager   |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

|                                      |   |
|--------------------------------------|---|
| Communications Cable                 | Micro-USB- to-USB A configuration/console Access cable  |
| Network Monitoring Port              | RJ45 Network port, Micro-USB Configuration port, USB A port supports a variety of Envirosense2 environmental and control modules. See Accessories>Management Hardware section for more information about these modules. |
| Network Compatibility                | 10 Mbps; 100 Mbps (Fast Ethernet)   |
| <b>FEATURES &amp; SPECIFICATIONS</b> |   |
| High Availability PDU Features       | Auto-Transfer Switching   |
| <b>STANDARDS &amp; COMPLIANCE</b>    |   |
| Product Certifications               | NOM (Mexico); UL 60950-1  |
| Product Compliance                   | RoHS; FCC Part 15 Class A (USA)   |
| <b>WARRANTY</b>                      |   |
| Product Warranty Period (Worldwide)  | 2-year limited warranty   |

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <https://www.tripplite.com/products/product-certification-agencies>