



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

## SmartPro 120V 3kVA 2.88kW Line-Interactive Sine Wave UPS, 2U Rack/Tower, Extended Run, Pre-installed WEBCARDLX Network Interface, LCD Display, USB, DB9 Serial

MODEL NUMBER: **SMART3000RMXLN**



### Highlights

- 3kVA / 3000VA / 2880W line interactive 2U rack/tower UPS, Sine Wave
- Extended runtime options up to 2880W, 0.96 Power Factor, 4 post mounting kit
- USB, RS232, EPO and pre-installed WEBCARDLX Network Interface
- 120V NEMA L5-30P input, 8 NEMA 5-15/20R & 1 L5-30R outlets
- To enable the Auto Probe feature, this product requires LX firmware update 15.5.2 or later to be installed

### Package Includes

- SMART3000RMXLN UPS system with Pre-installed Network Management Card
- USB, Serial & EPO cabling
- 4 post rackmount installation kit
- Instruction manual

### Description

Tripp Lite SmartPro Line Interactive UPS with enhanced LCD interface offers network-grade power protection for critical server, network and telecommunications equipment. Line Interactive Uninterruptible Power Supply (UPS) with built-in Auto-Voltage Regulation (AVR) actively corrects brownouts and overvoltages back to usable levels while maintaining a full battery charge in case of power failure. Tripp Lite's unique configuration excels in exceptionally poor-power environments with two separate levels of voltage boost to correct both slight undervoltages and severe brownout conditions. Interactive LCD interface reports UPS operating mode, detailed UPS and site-power data, plus enables a variety of UPS setup and configuration options. Super-fast switchover from line to battery power occurs within milliseconds to maintain operation of connected equipment without interruption or reboot. 96% line-mode efficiency offers reduced heat emissions and operating costs. Network management interfaces support communications via USB port, DB9 serial port and pre-installed WEBCARDLX network management interface card. The Java-free HTML5-based WEBCARDLX interface enables full remote access for site power and UPS status monitoring, configuration, control and email notifications via secure web browser, SNMP, telnet or SSH. It supports 10/100 Mbps auto-sensing for optimum communication with an Ethernet network. Optional EnviroSense2 modules (sold separately) provide a variety of environmental monitoring capabilities. Protocols supported include HTTP, HTTPS, SMTP, SNMPv1, SNMPv2, SNMPv3, telnet, SSH, FTP, DHCP and NTP. HID-compliant USB port enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Network communications ports enable detailed monitoring of equipment load levels, self-test data and utility power conditions. PowerAlert UPS monitoring software is available via free download. Switched output load banks enable scheduled and real-time remote reboot and load shedding of select outlets. Emergency Power Off (EPO) interface. LCD display panel easily rotates for viewing in rackmount or tower configurations. Audible alarm with push-button momentary alarm-cancel and silent-mode configuration options. Programmable self-test. Field-replaceable, hot-swappable battery modules.

### Features

- Tripp Lite SMART3000RMXLN line interactive 2U rack/tower UPS with 3000VA / 3kVA capacity and extended runtime options
- Line interactive UPS with Automatic Voltage Regulation (AVR) corrects brownouts and overvoltages from 83 to 145V
- NEMA L5-30P input plug; 8 NEMA 5-15/20R and 1 L5-30R output receptacles, Two independently switchable output load banks



- Maintains uninterrupted operation of connected networking equipment during blackouts, surges, brownouts and overvoltages
- High 96% efficiency rating in line-power mode offers reduced power consumption and BTU emissions
- Internal batteries offer 10 minutes at 50% load (1440W) and 3 minutes at 100% load (2880W)
- Extended runtime is available with optional BP48V24-2U (limit 1), BP48V60RT-3U (multi-pack compatible) and BP48V27-2US (multi-pack compatible) external battery packs
- External battery configurations require the use of Tripp Lite's External Battery Configuration Software (see manual)
- Hot-swappable, user-replaceable internal batteries and external battery packs can be replaced with no disruption to connected equipment
- Intelligent battery management system extends battery life
- Front panel LCD monitoring screen with MODE and ENTER buttons reports operating mode with 5-bar battery charge graphic, plus 7 selectable screens of detailed UPS and site power information
- LCD interface also supports a number of advanced user setup and operating preferences
- Ships with 4 post rackmount installation hardware; Optional 2POSTRMKITWM enables 2 post rackmount/wallmount installation; Optional 2-9USTAND enables tower placement
- Network interfaces support communications via built-in USB, DB9 serial / contact-closure and pre-installed WEBCARDLX network management card
- WEBCARDLX interface allows full remote access for power monitoring, configuration, control and email notifications via secure web browser, SNMP, Telnet, SSH or Command Line
- Reduce service calls with Auto Probe Autonomous Device Management. The Auto Probe feature (Firmware 15.5.2 and greater) of the LX Platform interface checks the connectivity status of any networked device and automatically takes one or more user-configured actions if the device fails to respond; actions include outlet reboot, set SNMP traps, SNMP OID sets, and even script execution when used in conjunction with the Tripp Lite PowerAlert Network Shutdown Agent (PANSA)
- Optional E2 sensors enable site monitoring of temperature, humidity and contact-closure status
- HID-compliant USB port enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- USB & Serial ports enable data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from [www.tripplite.com/poweralert](http://www.tripplite.com/poweralert)
- Built-in Emergency Power Off (EPO) interface with cable

## Specifications

| OVERVIEW                           |                  |
|------------------------------------|------------------|
| UPC Code                           | 037332177896     |
| UPS Type                           | Line-Interactive |
| INPUT                              |                  |
| Rated input current (Maximum Load) | 24A              |
| Nominal Input Voltage(s) Supported | 120V AC          |
| UPS Input Connection Type          | L5-30P           |
| UPS Input Cord Length (ft.)        | 10               |
| UPS Input Cord Length (m)          | 3.1              |
| Recommended Electrical Service     | 30A 120V         |
| Input Phase                        | Single-Phase     |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

| OUTPUT                                     |  |
|--|--|
| Output Volt Amp Capacity (VA)              | 3000   |
| Output Capacity (kVA)                      | 3.00   |
| Output Watt Capacity (Watts)               | 2880   |
| Output kW Capacity (kW)                    | 2.88   |
| Power Factor                               | .96  |
| Nominal Voltage Details                    | 120v nominal output in battery mode  |
| Frequency Compatibility                    | 60 Hz  |
| Output Voltage Regulation (Line Mode)      | +6%, -14%  |
| Output Voltage Regulation (Battery Mode)   | +/-5%  |
| Load Management Receptacles                | Two switchable single outlet 5-15/20R load banks   |
| Output Circuit Breakers                    | Two 20A output breakers protect 4 5-15/20R outlets each  |
| Output AC Waveform (AC Mode)               | Pure Sine wave   |
| Output AC Waveform (Battery Mode)          | Pure Sine wave   |
| Nominal Output Voltage(s) Supported        | 110V; 115V; 120V   |
| Output Receptacles                         | (8) 5-15/20R; (1) L5-30R   |
| Individually Controllable Load Banks       | Yes  |
| BATTERY                                    |  |
| Battery Type                               | Valve Regulated Lead Acid (VRLA)   |
| Full Load Runtime (min.)                   | 3 min. (2880w)   |
| Half Load Runtime (min.)                   | 10 min. (1440w)  |
| Expandable Battery Runtime                 | Extended runtime supported via optional external battery packs   |
| Expandable Runtime                         | Yes  |
| External Battery Pack Compatibility        | <a href="http://www.tripplite.com/External-48V-2U-Rack-Tower-Battery-Pack-Enclosure-DC-Cabling-select-UPS-Systems~BP48V24-2U">BP48V24-2U</a> (limit 1); <a href="http://www.tripplite.com/External-48V-3U-Rack-Tower-Battery-Pack-Enclosure-DC-Cabling-select-UPS-Systems~BP48V60RT-3U">BP48V60RT-3U</a> (multi-pack compatible); <a href="http://www.tripplite.com/External-48V-2U-Rack-Tower-Battery-Pack-for-UPS-Systems~BP48V27-2US">BP48V27-2US</a> (multi-pack compatible) |
| DC System Voltage (VDC)                    | 48   |
| Battery Recharge Rate (Included Batteries) | Less than 5 hours from 10 to 90% (typical, full load discharge)  |
| Battery Access                             | Front panel battery access door  |
| Internal UPS Replacement Battery Cartridge | <a href="http://www.tripplite.com/2U-UPS-Replacement-48VDC-Battery-Cartridge-for-Tripp-Lite-UPS-systems~RBC58-2U">RBC58-2U</a>   |
| Battery Replacement Description            | Hot-swappable, replaceable batteries   |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

| VOLTAGE REGULATION   |  |
|--|--|
| Voltage Regulation Description                                 | Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145   |
| Overvoltage Correction   | Input voltages between 127 and 145 are reduced by 12%  |
| Undervoltage Correction  | Input voltages between 108 and 96 are boosted by 12%   |
| Severe Undervoltage Correction                                 | Input voltages between 83 and 95 are boosted by 24%  |
| USER INTERFACE, ALERTS & CONTROLS                              |  |
| Front Panel LCD Display  | Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  |
| Switches   | 3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions. LX Platform Interface: Recessed reset switch for interface reboot and factory reset  |
| Alarm Cancel Operation   | Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available   |
| Audible Alarm  | Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions  |
| LED Indicators   | Network Link/Activity (Green): Flashes for network activity. Network Speed (Yellow): 10 Mbps (Flashing), 100 Mbps (On steady). LX Platform Interface Status: Normal Operation (Solid Green); Software Update (Alternating Green/Orange ~1/sec); Factory Reset (Alternating Green/Orange ~2/sec).   |
| SURGE / NOISE SUPPRESSION                                      |  |
| UPS AC Suppression Joule Rating                                | 570  |
| EMI / RFI AC Noise Suppression                                 | Yes  |
| AC Suppression Response Time                                   | Instantaneous  |
| PHYSICAL   |  |
| Primary Form Factor  | Rackmount  |
| Cooling Method   | Fan  |
| Included Mounting Accessory Description                        | Included 4POSTRAILKIT mounting bracket enables installation in 4 post racks from 20.5 to 36 inches (521 to 914mm)  |
| Installation Form Factors Supported with Included Accessories  | 4 post 19 inch rackmount   |
| Installation Form Factors Supported with Optional Accessories  | 2 post rackmount (&nbsp;<a class="productLink" href="//www.tripplite.com/2-Post-Rack-Mount-Wall-Mount-Adapter-Kit-select-Rack-Mount-UPS-Systems~2POSTRMKITWM">2POSTRMKITWM</a>&nbsp;); 4 post rackmount short-depth (&nbsp;<a class="productLink" href="//www.tripplite.com/4-Post-1U-Universal-Adjustable-Rack-Mount-Shelf-Kit-for-Wall-Mount-Racks~4POSTRAILKITWM">4POSTRAILKITWM</a>&nbsp;); Tower (&nbsp;<a class="productLink" href="//www.tripplite.com/2U-9U-Tower-Stand-Kit-select-Rack-Mount-UPS-Systems~2-9USTAND">2-9USTAND</a>&nbsp;); Wallmount (&nbsp;<a class="productLink" href="//www.tripplite.com/2-Post-Rack-Mount-Wall-Mount-Adapter-Kit-select-Rack-Mount-UPS-Systems~2POSTRMKITWM">2POSTRMKITWM</a>&nbsp;); |
| Minimum Required Rack Depth with External Battery Pack (cm)    | 67   |
| Minimum Required Rack Depth with External Battery Pack (in.)   | 26.5   |
| Minimum Required Rack Depth without External Battery Pack (cm) | 62   |



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

|   |  |
|---|--|
| Minimum Required Rack Depth without External Battery Pack (in.) | 24.5   |
| Optional Mounting Accessory Notes                               | Optional <a href="http://www.tripplite.com/2U-9U-Tower-Stand-Kit-select-Rack-Mount-UPS-Systems~2-9USTAND">2-9USTAND</a> enables upright tower UPS placement; <a href="http://www.tripplite.com/2-Post-Rack-Mount-Wall-Mount-Adapter-Kit-select-Rack-Mount-UPS-Systems~2POSTRMKITWM">2POSTRMKITWM</a> enables wall-mount and 2-post rackmount installation; <a href="http://www.tripplite.com/4-Post-1U-Universal-Adjustable-Rack-Mount-Shelf-Kit-for-Wall-Mount-Racks~4POSTRAILKITWM">4POSTRAILKITWM</a> enables installation in 4-post short-depth racks from 14.5 to 23.5 inches (368 to 597mm); <a href="http://www.tripplite.com/Heavy-Duty-2-post-Front-Mounting-Ear-Kit~UPSHDEARKIT">UPSHDEARKIT</a> enables installation in 2 or 4-post racks using front vertical rails only, without rear support |
| Primary UPS Depth (mm)  | 483  |
| Primary UPS Height (mm)   | 89   |
| Primary UPS Width (mm)  | 445  |
| Rack Height   | 2U   |
| Shipping Dimensions (hwd / cm)                                  | 21.59 x 61.72 x 53.85  |
| Shipping Dimensions (hwd / in.)                                 | 8.50 x 24.30 x 21.20   |
| Shipping Weight (kg)  | 40.82  |
| Shipping Weight (lbs.)  | 90.00  |
| UPS Housing Material  | Steel  |
| UPS Power Module Dimensions (hwd, cm)                           | 8.89 x 44.45 x 48.26   |
| UPS Power Module Dimensions (hwd, in.)                          | 3.50 x 17.50 x 19.00   |
| UPS Power Module Weight (kg)                                    | 33.02  |
| UPS Power Module Weight (lbs.)                                  | 72.8   |
| <b>ENVIRONMENTAL</b>  |  |
| Operating Temperature Range                                     | +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius  |
| Storage Temperature Range                                       | +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius   |
| Relative Humidity   | 0 to 95%, non-condensing   |
| AC Mode BTU / Hr. (Full Load)                                   | 409  |
| Battery Mode BTU / Hr. (Full Load)                              | 1736   |
| AC Mode Efficiency Rating (100% Load)                           | 96%  |
| Audible Noise   | 45 dBA maximum, front side 1m  |
| <b>COMMUNICATIONS</b>   |  |
| Network Management Cards  | <a href="http://www.tripplite.com/Web-Management-Accessory-Card~WEBCARDLX">WEBCARDLX</a>   |
| Network Monitoring Port Description                             | Includes pre-installed WEBCARDLX Network Management Card interface. RJ45 Network port, Micro-USB Configuration/Console port, USB A port supports a variety of Envirosense2 environmental and control modules. See Accessories>Management Hardware section for more information about these modules.  |
| PowerAlert Software   | For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at <a href="https://www.tripplite.com/poweralert">https://www.tripplite.com/poweralert</a>   |





**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

|   |   |
|---|---|
| Communications Cable  | Micro-USB, USB, DB9 and EPO cabling included  |
| WatchDog Compatibility                                      | Supports Watchdog application, OS and hard-reboot restart options for remote applications   |
| Network Monitoring Port                                     | RJ45 Network port, Micro-USB Configuration/Console port, USB A port supports a variety of EnviroSense2 environmental and control modules. See Accessories>Management Hardware section for more information about these modules.             |
| EPO Port  | RJ11 interface jack with 4-meter cable included. Supports normally open and normally closed EPO systems   |
| SNMP Compatibility  | SNMP V1, V2c, V3  |
| Network UPS Tools Compatibility                             | NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at <a href="https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp+Lite">https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite</a> |
| Network Compatibility                                       | 100 Mbps (Fast Ethernet)  |
| Network Management Card Description                         | Network management card included  |
| Communications Interface                                    | DB9 Serial; EPO (emergency power off); Pre-installed network card; Slot for SNMP/Web interface; USB (HID enabled)   |
| <b>LINE / BATTERY TRANSFER</b>                              |   |
| Transfer Time   | 5 milliseconds (AC to battery mode), 1 millisecond (Battery to AC mode)   |
| Low Voltage Transfer to Battery Power (Setpoint)            | 83  |
| High Voltage Transfer to Battery Power (Setpoint)           | 145   |
| <b>FEATURES &amp; SPECIFICATIONS</b>                        |   |
| Grounding Lug   | Back panel grounding lug  |
| Cold Start (Startup in Battery Mode During a Power Failure) | Cold-start operation supported  |
| High Availability UPS Features                              | Auto Probe Monitoring and Reboot (included); Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; Remote management; Sine wave output; Surge/noise protection  |
| Green Energy-Saving Features                                | Greater than 95% efficiency - GREEN UPS; Individually controllable load banks; Schedulable daily hours of economy mode operation  |
| <b>STANDARDS &amp; COMPLIANCE</b>                           |   |
| Product Certifications                                      | CSA (Canada); NOM (Mexico); UL 1778   |
| Product Compliance  | RoHS; FCC Part 15 Class A (USA)   |
| <b>WARRANTY</b>   |   |
| Product Warranty Period (Worldwide)                         | 2-year warranty, 3 year with registration. Note: <a href="https://www.tripplite.com/support/product-warranty-registration">Registration is required</a> for 3-year warranty.  |
| Connected Equipment Insurance (U.S., Canada & Puerto Rico)  | \$250,000 <a href="https://www.tripplite.com/support/insurance-policy">Ultimate Lifetime Insurance</a>  |

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

<https://www.tripplite.com/products/product-certification-agencies>