

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

900VA 480W Line-Interactive UPS with 6 Outlets - AVR, VS Series, 120V, 50/60 Hz, Tower

MODEL NUMBER: VS900T











Line-interactive UPS provides basic battery backup with AVR protection for your office computer, home theater setup or digital signage.

Features

900VA/480W/120V Battery Backup for PCs, Home Theater or Digital SignageThis 120V UPS with AVR protection provides reliable battery backup and AC power protection against blackouts, brownouts, surges and line noise that can damage valuable electronics or destroy data. The six-outlet 120V battery backup is ideal protection for your home office, media center or commerce components, including computers, routers, printers, HDTVs, Blu-ray players, game consoles, ATMs, security systems and digital signage equipment.

Allows Time to Back Up Critical Files During a BlackoutBackup support allows you to work through short power failures, and gives you enough time to safely save files and shut down your system in case of a prolonged blackout. Backup time varies according to load, but the line-interactive UPS system should keep an energy-efficient desktop computer with small LCD monitor powered as long as 44 minutes. During normal operation, incoming utility power keeps the replaceable internal battery fully charged, so backup power will always be available.

Connects Your Equipment to 6 NEMA 5-15R OutletsFour 5-15R outlets provide both battery backup and surge protection for your computer, monitor and other crucial components. The other two 5-15R outlets are surge-protected only for printers, scanners and other non-essential equipment. A high 95% line mode efficiency rating reduces BTU emissions, energy consumption and, ultimately, your energy costs.

Automatic Voltage Regulation (AVR) Corrects Low-Voltage ConditionsAVR protects your equipment from incremental hardware damage, data loss and performance problems caused by brownouts. The VS900T can correct brownouts as low as 89V and overvoltages as high as 145V back to nominal 120V power without drawing on the battery backup needed to support your equipment during a blackout.

316 Joules Fight Back Against Unexpected Power SurgesA 316-joule surge suppression rating protects connected components from the harmful effects of power surges.

Combats Electromagnetic Interference That Can Harm EquipmentVarious electromagnetic and radio sources found in virtually every home and business can cause disruptive interference on the AC line. Known as EMI (electromagnetic interference) and RFI (radio frequency interference), this line noise is a common cause of performance problems and can lead to incremental hardware damage, data corruption and audio/video transmission problems. The VS900T incorporates technology that filters out disruptive

Highlights

- Protects valuable equipment from dangers posed by brownouts, surges and line noise
- AVR battery backup allows time to save files and safely shut down during blackouts
- 6 NEMA 5-15R outlets provide power to PC, home theater or digital signage equipment
- Alarm and front-panel LEDs report online, battery, fault and overload conditions
- High 95% efficiency with low BTU ratings saves power and lowers your energy costs

Applications

- Protect your PC and other sensitive electronics against power surges, brownouts and blackouts
- Operate essential equipment during short-term power outages using battery backup power
- Shut down PCs, DVRs, routers and other equipment without data loss during long-term power outages

Package Includes

- VS900T 900VA 480W Line-Interactive UPS with 6 Outlets
- · Owner's manual



line noise so that it won't affect your equipment.

Easy-to-Read LEDs Report Real-Time UPS and Power StatusThree front-panel LED indicators monitor essential information, such as online, battery and fault modes. An audible alarm will sound in case of low battery, excessive load and fault condition.

Tower Form Factor for Easy Placement in Your Workspace or Media CenterThe long-lasting ABS housing fits easily on a desktop, shelf or anywhere else convenient to your workstation or home theater. The five-foot power cord with NEMA 5-15P plug connects to a properly grounded AC wall outlet.

Specifications

OVERVIEW			
UPC Code	037332212900		
UPS Type	Line-Interactive		
INPUT			
Rated input current (Maximum Load)	10A		
Nominal Input Voltage(s) Supported	120V AC		
UPS Input Connection Type	5-15P		
Input Circuit Breakers	10A		
UPS Input Cord Length (ft.)	5		
UPS Input Cord Length (m)	1.5		
Recommended Electrical Service	15A 120V		
Input Phase	Single-Phase		
OUTPUT			
Output Volt Amp Capacity (VA)	900		
Output Watt Capacity (Watts)	480		
Output Capacity Details	7.5A @ 120V. (LINE MODE) 110%+/- 10% @ 5 minutes; (BATTERY MODE) 110% +/- 10% @ 5 seconds		
Power Factor	0.53		
Nominal Voltage Details	120V sinusoidal in line mode and 120V PWM in battery mode		
Frequency Compatibility	60 Hz		
Frequency Compatibility Details	Output is regulated to +/-0.05Hz when input frequency exceeds +/-5Hz of nominal.		
Output Voltage Regulation (Line Mode)	120V (+9%, -12%)		
Output Voltage Regulation (Battery Mode)	120V (+/- 10%)		
UPS Output Receptacles (Surge Suppression Only)	4 UPS outlets, 2 surge-only outlets		
Output AC Waveform (AC Mode)	Sine wave		





·	-	
Output AC Waveform (Battery Mode)	PWM sine wave	
Nominal Output Voltage(s) Supported	110V; 115V; 120V	
Output Receptacles	(6) 5-15R	
Individually Controllable Load Banks	No	
BATTERY		
Battery Type	Valve Regulated Lead Acid (VRLA)	
Full Load Runtime (min.)	0.5 min. (480w)	
Half Load Runtime (min.)	3.8 min. (240w)	
Expandable Runtime	No	
DC System Voltage (VDC)	12	
Battery Recharge Rate (Included Batteries)	8 hours (10% to 90%)	
VOLTAGE REGULATION		
V 10 - 10 - 10	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 89 to 145	
Voltage Regulation Description		
Voltage Regulation Description Overvoltage Correction	Input voltages between 132 and 145 are reduced by 15%	
Overvoltage Correction	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18%	
Overvoltage Correction Undervoltage Correction	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18%	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Audible Alarm	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Audible Alarm LED Indicators	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status 3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red)	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status 3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red)	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status 3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red) 316 Instantaneous	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CONSWITCHES Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time EMI / RFI AC Noise Suppression	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status 3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red) 316 Instantaneous	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CON Switches Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time EMI / RFI AC Noise Suppression	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status 3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red) 316 Instantaneous Yes	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CONSIDER OF CONS	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status 3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red) 316 Instantaneous Yes	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CONSWITCHES Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time EMI / RFI AC Noise Suppression PHYSICAL Primary Form Factor Installation Form Factors Supported with Included Accessories	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status 3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red) 316 Instantaneous Yes Tower	
Overvoltage Correction Undervoltage Correction USER INTERFACE, ALERTS & CONSWITCHES Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time EMI / RFI AC Noise Suppression PHYSICAL Primary Form Factor Installation Form Factors Supported with Included Accessories Primary UPS Depth (mm)	Input voltages between 132 and 145 are reduced by 15% Input voltages between 89 and 108 are boosted by 18% TROLS Controls off/on power status Audible alarm indicates low-battery, fault, overload and replace-battery status 3 LEDs indicate online mode (green), battery mode (yellow) and fault mode (red) 316 Instantaneous Yes Tower Tower 300	





Shipping Weight (kg)	6.24	
UPS Housing Material	ABS	
UPS Power Module Dimensions (hwd, in.)	5.6 x 4 x 11.8	
UPS Power Module Weight (kg)	5.72	
UPS Power Module Weight (lbs.)	12.6	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +113 degrees Fahrenheit / -15 to +45 degrees Celsius	
Relative Humidity	0 to 90%, non-condensing	
AC Mode BTU / Hr. (Full Load)	66	
AC Mode Efficiency Rating (100% Load)	95%	
AC Economy Mode Efficiency Rating (100% Load)	0.95	
Operating Elevation (ft.)	6561 ft. (2000 m) above sea level	
COMMUNICATIONS		
Network UPS Tools Compatibility		
Network Management Card Description	Network management not supported	
Communications Interface	None	
LINE / BATTERY TRANSFER		
Transfer Time	6 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	89	
High Voltage Transfer to Battery Power (Setpoint)	145	
FEATURES & SPECIFICATIONS		
High Availability UPS Features	Automatic Voltage Regulation (AVR); Surge/noise protection	
STANDARDS & COMPLIANCE		
Product Certifications	CSA (Canada); NOM (Mexico); UL 1778	
Product Compliance	RoHS; FCC Part 15 Class A (USA)	
WARRANTY		
Product Warranty Period (U.S. & Canada)	3-year limited warranty	



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

Product Warranty Period (Latin America)	3-year limited warranty
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	3-year limited warranty

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies