

# MEGOHMMETERS

## 1000V DIGITAL

### MODEL 6527

*Insulation tester with DMM functions specially designed for testing wiring, small motors and other equipment*

### SPECIFICATIONS

MODEL	6527			
Range	4MΩ	40MΩ	400MΩ	4000MΩ(4GΩ)
<b>INSULATION TESTS (250V)</b>				
Resolution	0.001MΩ	0.01MΩ	0.1MΩ	1MΩ
Accuracy	±2% of rdg. ±10cts		±3% of rdg. ±5cts	±4% of rdg. ±5cts
Test Current	1mA test current into a 250kΩ load			
<b>INSULATION TESTS (500V)</b>				
Resolution	0.001MΩ	0.01MΩ	0.1MΩ	1MΩ
Accuracy	±2% of rdg. ±10cts		±2% of rdg. ±5cts	±4% of rdg. ±5cts
Test Current	1mA test current into a 500kΩ load			
<b>INSULATION TESTS (1000V)</b>				
Resolution	0.001MΩ	0.01MΩ	0.1MΩ	1MΩ
Accuracy	±3% of rdg. ±10cts	±2% of rdg. ±10cts	±2% of rdg. ±5cts	±4% of rdg. ±5cts
Test Current	1mA test current into a 1MΩ load			
<b>VOLTMETER RANGES (250V, 500V, &amp; 1000V)</b>				
V AC/DC	600V		1000V	
Resolution	1V			
Accuracy	DC	±0.8% of rdg. ±3cts		
	AC	±1.2% of rdg. ±10cts		
Input Impedance	DC	10MΩ		
	AC	10MΩ (40/400Hz)		
<b>RESISTANCE TESTS - OHMMETER</b>				
Range	0.0 to 400.0kΩ			
Resolution	0.1KΩ			
Accuracy	±1.2% of rdg. ±3cts			
<b>CONTINUITY TESTS</b>				
Range	0.00 to 400Ω			
Resolution	0.01Ω			0.1Ω
Accuracy	1.2% ±3cts			
Test Current	>200mA (0.2Ω / 2Ω)			
Test Lead Compensation	Yes: dedicated push-button			
Beeper	Yes: <35Ω ±3Ω			
<b>ELECTRICAL</b>				
Power Supply	Six 1.5V AA batteries – Alkaline recommended (included)			
<b>SAFETY</b>				
Safety Rating	EN 61557, 600V Cat. IV			
IP Protection	IP51			

Consult factory for NIST Calibration prices

### PRODUCT INCLUDES

Soft carrying case, set of (2) 5 ft color-coded (red/black) test leads with alligator clips, (1) black test probe and a user manual.



### FEATURES

- True Megohmmeter®
- Insulation test voltage selections of 250V, 500V and 1000V
- Measure insulation to 4000MΩ (4GΩ)
- TEST LOCK feature for time sensitive measurements up to 15 minutes
- Auto discharge after insulation test
- AC/DC voltmeter to 600V<sub>ac</sub>/1000V<sub>dc</sub>
- Ohmmeter to 400kΩ
- Continuity meter with >200mA test current
- Test lead resistance compensation for accurate low resistance measurements
- Auto HOLD function to “freeze” readings
- Large and bright dual display with blue backlight
- Auto Power OFF feature
- Ergonomic over-molded case with back-stand

CATALOG NO.	DESCRIPTION
2126.53	Megohmmeter Model 6527 (Digital 250V, 500V, 1000V, Continuity, 400kΩ, V)



# MEGOHMMETERS

## SELECTION CHART

AEMC MODEL NUMBER	AEMC CATALOG NUMBER	TEST VOLTAGE	INSULATION RANGE	RESISTANCE RANGE	CONTINUITY RANGE	CAPACITANCE RANGE	VOLTAGE DETECTION	POWER SOURCE	DISPLAY	DATAVIEW® SOFTWARE
6501	2126.51	500V	0.5 to 200MΩ	500kΩ	100Ω	—	600Vac	Hand-cranked	Analog	No
6503	2126.52	250V 500V 1000V	1 to 500MΩ 1 to 500MΩ 10 to 5000MΩ	—	—	—	600Vac	Hand-cranked	Analog	No
6527	2126.53	250V 500V 1000V	1kΩ to 4GΩ 1kΩ to 4GΩ 1kΩ to 4GΩ	400kΩ	400Ω	—	600Vac 1000Vdc	6 x AA Alkaline Batteries	Digital/ Analog	No
6522	2155.51	250V 500V 1000V	50kΩ to 10GΩ 100kΩ to 20GΩ 200kΩ to 40GΩ	—	10Ω	—	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6528	2126.54	250V 500V 1000V	0.050MΩ to 4200MΩ 0.100MΩ to 4200MΩ 0.20MΩ to 11GΩ	0 to 420kΩ	0 to 40Ω (200mA test current ≤ 2Ω)	—	700Vac 700Vac/dc	6 x AA Alkaline Batteries	Digital	No
6529	2126.55	50V 100V 250V 500V 1000V	0.010MΩ to 420MΩ 0.020MΩ to 420MΩ 0.050MΩ to 420MΩ 0.100MΩ to 4200MΩ 0.20MΩ to 11GΩ	0 to 420kΩ	0 to 40Ω (200mA test current ≤ 2Ω)	—	700Vac 700Vac/dc	6 x AA Alkaline Batteries	Digital	No
6524	2155.52	50V 100V 250V 500V 1000V	10kΩ to 10GΩ 20kΩ to 20GΩ 50kΩ to 50GΩ 100kΩ to 100GΩ 200kΩ to 200GΩ	1000kΩ	10Ω, 100Ω	—	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6526	2155.53	50V 100V 250V 500V 1000V	10kΩ to 10GΩ 20kΩ to 20GΩ 50kΩ to 50GΩ 100kΩ to 100GΩ 200kΩ to 200GΩ	1000kΩ	10Ω, 100Ω	0.1n to 10μF	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6532	2155.54	50V 100V	10kΩ to 10GΩ 20kΩ to 20GΩ	1000kΩ	10Ω, 100Ω	0.1n to 10μF	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6534	2155.55	10V 25V 100V 250V 500V	2kΩ to 1GΩ 5kΩ to 2GΩ 10kΩ to 10GΩ 50kΩ to 25GΩ 100kΩ to 50GΩ	1000kΩ	10Ω, 100Ω	—	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6536	2155.56	10V 100V	2kΩ to 20GΩ	1000kΩ	10Ω, 100Ω	—	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6536 ESD Floor Kit	2155.57	(variable in 1V steps)								
1050	2130.01	50V 100V 250V 500V 1000V	2kΩ to 200GΩ 4kΩ to 400GΩ 10kΩ to 1TΩ 20kΩ to 2TΩ 40kΩ to 4TΩ	400kΩ	40Ω	0.005 to 4.999μF	1000Vac/dc	8 x 1.5V C Cell Batteries	Digital/ Analog	No
1060	2130.03	50V 100V 250V 500V 1000V	2kΩ to 200GΩ 4kΩ to 400GΩ 10kΩ to 1TΩ 20kΩ to 2TΩ 40kΩ to 4TΩ	400kΩ	40Ω	0.005 to 4.999μF	1000Vac/dc	Rechargeable NiMH Battery	Digital/ Analog	Yes
6505	2130.18	500V 1000V 2500V 5000V	10kΩ to 2TΩ 10kΩ to 4TΩ 10kΩ to 10TΩ 10kΩ to 10TΩ	—	—	0.001 to 49.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	No
5050	2130.20	500V 1000V 2500V 5000V	10kΩ to 2TΩ 10kΩ to 4TΩ 10kΩ to 10TΩ 10kΩ to 10TΩ	—	—	0.001 to 49.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	No
5060	2130.21	500V 1000V 2500V 5000V	10kΩ to 2TΩ 10kΩ to 4TΩ 10kΩ to 10TΩ 10kΩ to 10TΩ	—	—	0.001 to 49.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes
5070	2130.30	500V 1000V 2500V 5000V	10kΩ to 2TΩ 10kΩ to 4TΩ 10kΩ to 10TΩ 10kΩ to 10TΩ	—	—	0.001 to 49.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Graphic/ Digital	Yes
6550	2130.31	500V 1000V 2500V 5000V 10,000V	10kΩ to 2000GΩ 10kΩ to 4000GΩ 10kΩ to 10,000GΩ 10kΩ to 15,000GΩ 10kΩ to 25,000GΩ	—	—	0.001 to 19.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes
6555	2130.32	500V 1000V 2500V 5000V 10,000V 15,000V	10kΩ to 2000GΩ 10kΩ to 4000GΩ 10kΩ to 10,000GΩ 10kΩ to 15,000GΩ 10kΩ to 25,000GΩ 10kΩ to 30,000GΩ	—	—	0.001 to 19.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes

Consult factory for NIST Calibration prices