

MEGOHMMETERS

5000V DIGITAL/ANALOG

MODELS 5050 & 5060

Designed with the highest level of built-in safety features

SPECIFICATIONS

MODELS	5050	5060
INSULATION TESTS		
Test Voltage	500V 1000V 2500V 5000V	10kΩ to 2000GΩ (2TΩ) 10kΩ to 4000GΩ (4TΩ) 10kΩ to 10,000GΩ (10TΩ) 10kΩ to 10,000GΩ (10TΩ)
User Selectable Test Voltage	Programmable: 40 to 1000V: 10V increments; 1000 to 5100V: 100V increments	
Accuracy	10kΩ to 399.9GΩ 400GΩ to 10TΩ	±5% of Reading ±3cts ±15% of Reading ±10cts
Voltage Test/Safety Check	2500VAC/4000VDC	
Voltage Warning Indicator	Yes >25V	
Test Inhibition	Yes — selectable at 3, 10 or 20% of test voltage	
Smooth Function (user selectable)	Digital filtering stabilizes display readings	
COMMUNICATION		
Storage of Readings over Time R(t)	4kB memory	128kB memory
Storage of Test Results	20 readings	1500 readings
Communication Port	—	Serial and RS-232 to USB adapter (included)
PC Software/Report Generation	—	DataView® (included)
ELECTRICAL		
Power Source	One 9.6V NiMH battery pack (included) Line power: 85 to 256V (50/60Hz)	
SAFETY		
Safety Rating / Ingress Protection	EN 61010-1, 600V, CAT III 1000V / IP53	

Consult factory for NIST Calibration prices

PRODUCT INCLUDES

5050, 5060 & 5070

Extra large classic tool bag, set of (3) 10 ft (5kV) color-coded leads (red/black/blue) with integral 5000V rated hippo clips, (1) guard terminal jumper lead, US 115V power cord, 9.6V NiMH rechargeable battery pack and a user manual.

CATALOG #2119.45

PC RS-232 DB9 F/F 6 ft Null Modem Cable
(Models 5060 & 5070)

CATALOG #5000.60

Adapter RS-232 to USB 2.0
(Models 5060 & 5070)

USB THUMB DRIVE

Supplied with
DataView® software
and a user manual
(Models 5060 & 5070)



CATALOG #2119.45, #5000.60 & USB DRIVE
(5060 & 5070 only)



DataView®
5060 only

FEATURES

- True Megohmmeter®
- Test voltage selections of 500V, 1000V, 2500V and 5000V
- Variable test voltage from 50 to 5100V (model 5060)
- Wide measurement range up to 10TΩ
- Automatic discharge at the completion of the test
- Measure AC voltage up to 4000V
- Automatic test inhibit if live voltage detected above a set value
- Programmable alarms for all functions
- Automatic calculation of DAR, PI and DD ratios
- Large, backlit LCD screen with digital display and bargraph
- Measures capacitance up to 49.99µf
- Stores up to 1500 measurements (model 5060)
- Includes DataView® software for data retrieval, real-time display, analysis and report generation

CATALOG NO.	DESCRIPTION
2130.20	Megohmmeter Model 5050 (Digital, Analog Bargraph, Backlight, Alarm, Timer, 500V, 1000V, 2500V, 5000V, Auto DAR/PI/DD)
2130.21	Megohmmeter Model 5060 (Digital, Analog Bargraph, Backlight, Alarm, Timer, 500V, 1000V, 2500V, 5000V, Auto DAR/PI/DD, RS-232 w/ DataView® Software)



MEGOHMMETERS

SELECTION CHART

AEMC MODEL NUMBER	AEMC CATALOG NUMBER	TEST VOLTAGE	INSULATION RANGE	RESISTANCE RANGE	CONTINUITY RANGE	CAPACITANCE RANGE	VOLTAGE DETECTION	POWER SOURCE	DISPLAY	DATAVIEW® SOFTWARE
6501	2126.51	500V	0.5 to 200MΩ	500kΩ	100Ω	—	600Vac	Hand-cranked	Analog	No
6503	2126.52	250V 500V 1000V	1 to 500MΩ 1 to 500MΩ 10 to 5000MΩ	—	—	—	600Vac	Hand-cranked	Analog	No
6527	2126.53	250V 500V 1000V	1kΩ to 4GΩ 1kΩ to 4GΩ 1kΩ to 4GΩ	400kΩ	400Ω	—	600Vac 1000Vdc	6 x AA Alkaline Batteries	Digital/ Analog	No
6522	2155.51	250V 500V 1000V	50kΩ to 10GΩ 100kΩ to 20GΩ 200kΩ to 40GΩ	—	10Ω	—	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6528	2126.54	250V 500V 1000V	0.050MΩ to 4200MΩ 0.100MΩ to 4200MΩ 0.20MΩ to 11GΩ	0 to 420kΩ	0 to 40Ω (200mA test current ≤ 2Ω)	—	700Vac 700Vac/dc	6 x AA Alkaline Batteries	Digital	No
6529	2126.55	50V 100V 250V 500V 1000V	0.010MΩ to 420MΩ 0.020MΩ to 420MΩ 0.050MΩ to 420MΩ 0.100MΩ to 4200MΩ 0.20MΩ to 11GΩ	0 to 420kΩ	0 to 40Ω (200mA test current ≤ 2Ω)	—	700Vac 700Vac/dc	6 x AA Alkaline Batteries	Digital	No
6524	2155.52	50V 100V 250V 500V 1000V	10kΩ to 10GΩ 20kΩ to 20GΩ 50kΩ to 50GΩ 100kΩ to 100GΩ 200kΩ to 200GΩ	1000kΩ	10Ω, 100Ω	—	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6526	2155.53	50V 100V 250V 500V 1000V	10kΩ to 10GΩ 20kΩ to 20GΩ 50kΩ to 50GΩ 100kΩ to 100GΩ 200kΩ to 200GΩ	1000kΩ	10Ω, 100Ω	0.1n to 10μF	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6532	2155.54	50V 100V	10kΩ to 10GΩ 20kΩ to 20GΩ	1000kΩ	10Ω, 100Ω	0.1n to 10μF	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6534	2155.55	10V 25V 100V 250V 500V	2kΩ to 1GΩ 5kΩ to 2GΩ 10kΩ to 10GΩ 50kΩ to 25GΩ 100kΩ to 50GΩ	1000kΩ	10Ω, 100Ω	—	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6536	2155.56	10V 100V	2kΩ to 20GΩ	1000kΩ	10Ω, 100Ω	—	700Vac/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6536 ESD Floor Kit	2155.57	(variable in 1V steps)								
1050	2130.01	50V 100V 250V 500V 1000V	2kΩ to 200GΩ 4kΩ to 400GΩ 10kΩ to 1TΩ 20kΩ to 2TΩ 40kΩ to 4TΩ	400kΩ	40Ω	0.005 to 4.999μF	1000Vac/dc	8 x 1.5V C Cell Batteries	Digital/ Analog	No
1060	2130.03	50V 100V 250V 500V 1000V	2kΩ to 200GΩ 4kΩ to 400GΩ 10kΩ to 1TΩ 20kΩ to 2TΩ 40kΩ to 4TΩ	400kΩ	40Ω	0.005 to 4.999μF	1000Vac/dc	Rechargeable NiMH Battery	Digital/ Analog	Yes
6505	2130.18	500V 1000V 2500V 5000V	10kΩ to 2TΩ 10kΩ to 4TΩ 10kΩ to 10TΩ 10kΩ to 10TΩ	—	—	0.001 to 49.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	No
5050	2130.20	500V 1000V 2500V 5000V	10kΩ to 2TΩ 10kΩ to 4TΩ 10kΩ to 10TΩ 10kΩ to 10TΩ	—	—	0.001 to 49.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	No
5060	2130.21	500V 1000V 2500V 5000V	10kΩ to 2TΩ 10kΩ to 4TΩ 10kΩ to 10TΩ 10kΩ to 10TΩ	—	—	0.001 to 49.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes
5070	2130.30	500V 1000V 2500V 5000V	10kΩ to 2TΩ 10kΩ to 4TΩ 10kΩ to 10TΩ 10kΩ to 10TΩ	—	—	0.001 to 49.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Graphic/ Digital	Yes
6550	2130.31	500V 1000V 2500V 5000V 10,000V	10kΩ to 2000GΩ 10kΩ to 4000GΩ 10kΩ to 10,000GΩ 10kΩ to 15,000GΩ 10kΩ to 25,000GΩ	—	—	0.001 to 19.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes
6555	2130.32	500V 1000V 2500V 5000V 10,000V 15,000V	10kΩ to 2000GΩ 10kΩ to 4000GΩ 10kΩ to 10,000GΩ 10kΩ to 15,000GΩ 10kΩ to 25,000GΩ 10kΩ to 30,000GΩ	—	—	0.001 to 19.99μF	2500Vac 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes

Consult factory for NIST Calibration prices