

Model CC 500

General Purpose BNC &N Type Adapter Kit

Data Sheet

CC 500

General Purpose BNC & N Type Adapter Kit



Features:

- BNC & N Type 50Ω Connectors
- · Gold plated center contacts
- Storage case


Applications:

- Production Testing Stations
- Service & Repair Facilities
- Educational Test Benches

General Purpose Adapter Accessory Kit for Basic RF Interconnection Needs:

Model CC 500 General Purpose BNC & N Type Adapter Kit provides a comprehensive range of in-series and between-series BNC and N Type coaxial adapters for basic RF testing and troubleshooting needs. The 12 piece kit, packaged in a convenient foam-lined storage case for easy selection and use, is ideal for all popular instruments. The kit contains the most commonly used BNC and N Type adapters for everyday testing. All components feature 50Ω impedance, gold plated center contacts, and low VSWR to ensure accurate repeatable measurements.

Kit Contents:



			Frequency	
Itm	Description	Qty.	Range	VSWR Max.
a.	BNC Tee female-male-female	1	DC - 4 GHz	N/A
b.	N Type female-female	1	DC - 8 GHz	1.30:1 @ 8 GHz
c.	N Type male-male	1	DC - 8 GHz	1.30:1 @ 8 GHz
d.	N Type Tee female-male-female	1	DC - 8 GHz	N/A
e.	BNC female to N Type male	1	DC - 4 GHz	1.30:1 @ 4 GHz
f.	BNC male to N Type female	1	DC - 4 GHz	1.30:1 @ 4 GHz
g.	BNC female-female	1	DC - 4 GHz	1.30:1 @ 4 GHz
h.	BNC male-male	1	DC - 4 GHz	1.30:1 @ 4 GHz
i.	BNC female to N Type female	1	DC - 4 GHz	1.30:1 @ 4 GHz
j.	BNC Tee female-female-female	1	DC - 4 GHz	N/A
k.	N Type Tee female-female-female	1	DC - 8 GHz	N/A
l.	N Type Right-Angle male-female	1	DC - 8 GHz	1.35:1 @ 8 GHz



205 Westwood Ave Long Branch, NJ 07740 1-877-742-TEST (8378) Fax: (732) 222-7088 salesteam@Tequipment.NET

Specifications subject to change without notice