


## TECHNICAL DATA SHEET

Part#: 554A-US

Pliers - Stress Relief -.208" x .25" Tip  
Designed to form stress relief for transistor and resistor leads

The 554A-US 5" stress relief forming plier is designed to form stress relief for transistor and resistor leads. The tool design will make consistent stand off in a variety of components. It's recommended for .025" and smaller wire. It features an ergonomically molded antimicrobial Anti-Static grip (10<sup>10</sup> ohms/sq surface resistivity) with dual leaf springs.

|                       |                          |
|-----------------------|--------------------------|
| • Precision Level     | ★★★★★                    |
| • Material            | Carbon                   |
| • Surface Resistivity | 10 <sup>10</sup> ohms/sq |
| • Shape               | Straight                 |
| • Type of Cut         | n/a                      |
| • Cutting Capacity    | n/a                      |
| • Blade Angle         |                          |
| • Blade Length        | .924"                    |
| • Body Width          | 0.42" (10.5mm)           |
| • Body Height         |                          |
| • OAL                 | 5" (125mm)               |
| • Weight (OZ)         | 5                        |
| • UPC                 | 662847007385             |
| • Schedule B          | 8203.20.60.30            |
| • ECCN                | EAR99                    |
| • UNSPSC Code         |                          |
| • Country of Origin   | USA                      |
| • Group               | Small Frame              |



**EXCELTA**<sup>®</sup>  
CORPORATION

**554A-US**  
Component Forming  
"Stress Relief Bender"