

Tripp Lite
1111 W. 35th Street

Chicago, IL 60609 USA Telephone: 773.869.1234 www.tripplite.com

# 2-Port USB 3.0 Peripheral Sharing Switch - SuperSpeed

MODEL NUMBER: U359-002











Connects a single USB printer or other peripheral to 2 computers simultaneously to save time, money and precious workspace.

#### **Features**

USB Sharing Switch Connects 2 Computers to One USB Printer, Scanner or Other DeviceThis compact 2-port USB peripheral-sharing switch lets you share one USB 3.0 peripheral between two computers in your home or small office. This eliminates the cost and effort of picking out and buying two printers, two scanners, two external hard drives, etc., as well as the problem of where to put them and their cables. By sharing a USB 3.0 printer or webcam between two computers, you save time, money and precious workspace. Maximum distance from host device to peripheral is 16-ft. (4.88 m).

Supports SuperSpeed USB 3.0 to Ensure Fast Data TransfersThis USB 3.0 sharing switch supports USB 3.0 data transfer rates up to 5 Gbps, which is 10 times faster than USB 2.0. It is especially recommended for high-bandwidth USB 3.0 devices, such as security cameras and high-resolution webcams. The USB 3.0 peripheral-sharing switch is backward compatible with previous USB generations, so you can continue using older peripherals while getting maximum performance from current devices.

**Switch Between Computers with a Quick Touch of a Button**Easy one-touch port switching lets you switch from one computer to the other just by pressing the buttons on top of the unit. Blue LEDs indicate which computer is currently in control of the connected USB 3.0 peripheral.

Ready to Use Right from the Package, So You Can Plug and Play Immediately The USB sharing switch requires no external power supply or software and drivers to download and install. Just connect your USB 3.0 peripheral device to the switch's USB-A port and the computers to the switch's USB-B ports with user-supplied USB 3.0 cables. The USB 3.0 sharing switch supports all USB-enabled operating systems.

#### **Highlights**

- Share a printer, scanner, hard drive, webcam or other USB device with 2 computers
- Supports SuperSpeed USB 3.0 speeds up to 5 Gbps to ensure fast data transfers
- Easy one-touch control lets you switch between computers using manual buttons
- Backward compatible with USB 2.0 and 1.1 devices, so you can use older peripherals
- Plug-and-play operation with no software required for easy, immediate installation

#### **Applications**

- Switch one printer or scanner between 2 computers to save space in the office
- Connect an external hard drive, so both computers can access the same data
- Control 2 computers using the same USB keyboard/mouse combo
- Connect a webcam or security camera to monitor inventory or an office lobby from multiple computers

#### System Requirements

- Up to 2 computers with USB-A ports
- Peripheral with USB-A port

### Package Includes

- U359-002 2-Port USB 3.0 Peripheral Sharing Switch -SuperSpeed
- Owner's manual

## **Specifications**

OVERVIEW	
UPC Code	037332224774



Bus Powered	Yes	
USER INTERFACE, ALERTS & CONTROLS		
LED Indicators	Blue (Display Control)	
PHYSICAL		
Material of Construction	ABS	
Color	Black	
Shipping Dimensions (hwd / cm)	3.71 x 7.80 x 6.30	
Shipping Dimensions (hwd / in.)	1.46 x 3.07 x 2.48	
Shipping Weight (kg)	0.06	
Shipping Weight (lbs.)	0.14	
Unit Dimensions (hwd / in.)	2.8 x 2.2 x 0.8	
Unit Dimensions (hwd / cm)	7.1 x 5.6 x 2	
Unit Packaging Type	Вох	
Unit Weight (lbs.)	0.01	
Unit Weight (kg)	0.00	
ENVIRONMENTAL		
Operating Temperature Range	32 to 104 F (0 to 40 C)	
Storage Temperature Range	14 to 131 F (-10 to 55 C)	
Operating Humidity Range	5% to 90% RH, Non-Condensing	
Storage Humidity Range	5% to 95% RH, Non-Condensing	
0 , 0		
CONNECTIONS	3	
CONNECTIONS  Number of Ports	3 USB 3.0 A (FEMALE)	
CONNECTIONS  Number of Ports  Side A - Connector 1		
	USB 3.0 A (FEMALE)	
CONNECTIONS  Number of Ports  Side A - Connector 1  Side B - Connector 1	USB 3.0 A (FEMALE)  (2) USB 3.0 B (FEMALE)	
CONNECTIONS  Number of Ports  Side A - Connector 1  Side B - Connector 1  Connector Plating	USB 3.0 A (FEMALE)  (2) USB 3.0 B (FEMALE)	
CONNECTIONS  Number of Ports  Side A - Connector 1  Side B - Connector 1  Connector Plating  FEATURES & SPECIFICATIONS	USB 3.0 A (FEMALE)  (2) USB 3.0 B (FEMALE)  Nickel	



**Tripp Lite**1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

Product Compliance	RoHS; CE (Europe); REACH; FCC (USA)
WARRANTY	
Product Warranty Period (Worldwide)	3-year limited warranty

© 2022 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <a href="https://www.tripplite.com/products/product-certification-agencies">https://www.tripplite.com/products/product-certification-agencies</a>